

Package ‘spant’

March 30, 2022

Type Package

Title MR Spectroscopy Analysis Tools

Version 1.20.0

Date 2022-03-29

Description Tools for reading, visualising and processing Magnetic Resonance Spectroscopy data. The package includes methods for spectral fitting: Wilson (2021) <[DOI:10.1002/mrm.28385](https://doi.org/10.1002/mrm.28385)> and spectral alignment: Wilson (2018) <[DOI:10.1002/mrm.27605](https://doi.org/10.1002/mrm.27605)>.

BugReports <https://github.com/martin3141/spant/issues/>

License GPL-3

RoxygenNote 7.1.2

NeedsCompilation yes

LazyData yes

Depends R (>= 2.10)

Imports abind, plyr, pracma, stringr, expm, signal, minpack.lm, utils, graphics, grDevices, smoother, magrittr, ptw, mmand, RNifti, RNiftyReg, fields, numDeriv, nloptr, irlba, jsonlite

Suggests viridisLite, shiny, miniUI, knitr, rmarkdown, testthat, ragg, doParallel

VignetteBuilder knitr

Encoding UTF-8

Language en-GB

URL <https://martin3141.github.io/spant/>,
<https://github.com/martin3141/spant/>

Author Martin Wilson [cre, aut] (<<https://orcid.org/0000-0002-2089-3956>>),
Yong Wang [ctb],
John Muschelli [ctb]

Maintainer Martin Wilson <martin@pipegrep.co.uk>

Repository CRAN

Date/Publication 2022-03-30 13:10:02 UTC

R topics documented:

spant-package	7
abfit_opts	8
abfit_opts_v1_9_0	11
acquire	12
add_noise	12
align	13
apodise_xy	13
append_basis	14
append_coils	14
append_dyns	15
apply_axes	15
apply_mrs	16
apply_pvc	16
Arg.mrs_data	17
array2mrs_data	17
auto_phase	18
back_extrap_ar	19
basis2mrs_data	19
bbase	20
bc_als	21
bc_constant	21
beta2lw	22
calc_coil_noise_cor	22
calc_coil_noise_sd	23
calc_ed_from_lambda	23
calc_peak_info_vec	24
calc_sd_poly	24
calc_spec_diff	25
calc_spec_snr	25
check_lcm	26
check_tqn	26
circ_mask	27
collapse_to_dyns	27
comb_coils	28
comb_fit_list_fit_tables	29
comb_fit_list_result_tables	29
comb_fit_tables	30
comb_metab_ref	30
Conj.mrs_data	31
conv_mrs	31
crop_spec	32
crop_td_pts	32
crop_xy	33
crossprod_3d	33
decimate_mrs_fd	34
decimate_mrs_td	34

def_acq_paras	35
def_fs	36
def_ft	36
def_N	36
def_nuc	37
def_ref	37
dicom_reader	37
diff_mrs	38
downsample_mrs_fd	39
downsample_mrs_td	39
ecc	40
elliptical_mask	40
est_noise_sd	41
fd2td	41
fd_conv_filt	42
fit_amps	42
fit_diags	43
fit_mrs	43
fit_res2csv	45
fp_phase	45
fp_phase_correct	46
fp_scale	46
fs	47
ft_dyns	47
ft_shift	48
ft_shift_mat	48
gausswin_2d	49
gen_F	49
gen_F_xy	50
get_1h_brain_basis_paras	50
get_1h_brain_basis_paras_v1	51
get_1h_brain_basis_paras_v2	51
get_1h_brain_basis_paras_v3	52
get_2d_psf	52
get_acq_paras	53
get_dyns	53
get_even_dyns	54
get_fh_dyns	54
get_fit_map	55
get_fp	55
get_guassian_pulse	56
get_head_dyns	56
get_lcm_cmd	57
get_metab	57
get_mol_names	57
get_mol_paras	58
get_mrsi2d_seg	58
get_mrsi_voi	59

get_mrsi_voxel	59
get_mrsi_voxel_xy_psf	60
get_mrs_affine	60
get_odd_dyns	61
get_ref	61
get_seg_ind	62
get_sh_dyns	62
get_slice	63
get_subset	63
get_svs_voi	64
get_tail_dyns	65
get_td_amp	65
get_tqn_cmd	66
get_uncoupled_mol	66
get_voi_cog	67
get_voi_seg	67
get_voi_seg_psf	68
get_voxel	68
gridplot	69
gridplot.mrs_data	69
grid_shift_xy	70
hsvd	70
hsvd_filt	71
hsvd_vec	72
hz	72
ift_shift	73
ift_shift_mat	73
Im.mrs_data	74
image.mrs_data	74
img2kspace_xy	75
interleave_dyns	76
int_spec	76
inv_even_dyns	77
inv_odd_dyns	77
is.def	78
is_fd	78
kspace2img_xy	79
l2_reg	79
lb	80
lw2alpha	81
lw2beta	81
mask_dyns	82
mask_xy	82
mask_xy_mat	83
mat2mrs_data	83
max_mrs	84
max_mrs_interp	84
mean.mrs_data	85

mean_dyns	85
mean_dyn_blocks	86
mean_dyn_pairs	86
mean_mrs_list	87
median_dyns	87
Mod.mrs_data	88
mrs_data2basis	88
mrs_data2mat	89
mrs_data2vec	89
mvfftshift	90
mvifftshift	90
n2coord	91
Ncoils	91
Ndyns	91
nifti_flip_lr	92
Npts	92
Nspec	93
Nx	93
Ny	93
Nz	94
ortho3	94
ortho3_inter	95
peak_info	96
pg_extrap_xy	97
phase	98
plot.fit_result	98
plot.mrs_data	100
plot_bc	102
plot_slice_fit	102
plot_slice_fit_inter	103
plot_slice_map	103
plot_slice_map_inter	104
plot_voi_overlay	106
plot_voi_overlay_seg	106
ppm	107
precomp	107
print.fit_result	108
print.mrs_data	108
qn_states	109
rats	109
Re.mrs_data	110
read_basis	111
read_basis_ac	111
read_ima_coil_dir	112
read_ima_dyn_dir	112
read_lcm_coord	113
read_mrs	113
read_mrs_tqn	114

read_siemens_txt_hdr	115
read_tqn_fit	116
read_tqn_result	116
recon_twix_2d_mrsi	117
rectangular_mask	117
rep_array_dim	118
rep_dyn	118
rep_mrs	119
resample_img	119
resample_voi	120
reslice_to_mrs	120
reson_table2mrs_data	121
re_weighting	121
rm_dyns	122
scale_amp_molal_pvc	122
scale_amp_molar	123
scale_amp_ratio	123
scale_amp_water_ratio	124
scale_mrs_amp	124
scale_spec	125
sd	125
sd.mrs_data	126
seconds	126
seq_cpmg_ideal	127
seq_mega_press_ideal	127
seq_press_ideal	128
seq_pulse_acquire	129
seq_pulse_acquire_31p	129
seq_slaser_ideal	130
seq_spin_echo_ideal	130
seq_spin_echo_ideal_31p	131
seq_steam_ideal	131
set_def_acq_paras	132
set_lcm_cmd	132
set_lw	133
set_mask_xy_mat	133
set_precomp_mode	134
set_precomp_verbose	134
set_ref	134
set_td_pts	135
set_tqn_cmd	135
shift	136
shift_basis	136
sim_basis	137
sim_basis_1h_brain	137
sim_basis_1h_brain_press	138
sim_basis_tqn	139
sim_brain_1h	139

sim_mol	140
sim_noise	141
sim_resonances	142
sim_zero	143
sort_basis	143
spant_abfit_benchmark	144
spant_mpress_drift	144
spant_simulation_benchmark	145
spec_op	145
spin_sys	146
spm_pve2categorical	146
ssp	147
stackplot	147
stackplot.fit_result	148
stackplot.mrs_data	149
sub_mean_dyns	151
sum_coils	151
sum_dyns	152
sum_mrs	152
sum_mrs_list	153
svs_1h_brain_analysis	153
svs_1h_brain_batch_analysis	154
td2fd	155
tdsr	156
td_conv_filt	156
varpro_3_para_opts	157
varpro_basic_opts	158
varpro_opts	158
vec2mrs_data	159
write_basis	160
write_basis_tqn	160
write_mrs	161
write_mrs_nifti	161
zero_fade_spec	162
zero_nzoc	162
zf	163
zf_xy	163

Index**165**

spant-package

*spant: spectroscopy analysis tools.***Description**

spant provides a set of tools for reading, visualising and processing Magnetic Resonance Spectroscopy (MRS) data.

Details

To get started with spant, take a look at the introduction vignette:

```
vignette("spant-intro", package="spant")
```

Full list of vignettes:

```
browseVignettes(package = "spant")
```

Full list of functions:

```
help(package = spant, help_type = "html")
```

An online version of the documentation is available from:

<https://martin3141.github.io/spant/>

Author(s)

Maintainer: Martin Wilson <martin@pipegrep.co.uk> ([ORCID](#))

Other contributors:

- Yong Wang [contributor]
- John Muschelli [contributor]

See Also

Useful links:

- <https://martin3141.github.io/spant/>
- <https://github.com/martin3141/spant/>
- Report bugs at <https://github.com/martin3141/spant/issues/>

abfit_opts

Return a list of options for an ABfit analysis.

Description

Return a list of options for an ABfit analysis.

Usage

```
abfit_opts(  
  init_damping = 5,  
  maxiters = 1024,  
  max_shift = 0.078,  
  max_damping = 15,  
  max_phase = 360,  
  lambda = NULL,  
  ppm_left = 4,  
  ppm_right = 0.2,  
)
```



```

    zp = TRUE,
    bl_ed_pppm = 2,
    auto_bl_flex = TRUE,
    bl_comps_pppm = 15,
    export_sp_fit = FALSE,
    max_asym = 0.25,
    max_basis_shift = 0.0078,
    max_basis_damping = 2,
    maxiters_pre = 1000,
    algo_pre = "NLOPT_LN_NELDERMEAD",
    min_bl_ed_pppm = NULL,
    max_bl_ed_pppm = 7,
    auto_bl_flex_n = 20,
    pre_fit_bl_ed_pppm = 1,
    remove_lip_mm_prefit = FALSE,
    pre_align = TRUE,
    max_pre_align_shift = 0.1,
    pre_align_ref_freqs = c(2.01, 3.03, 3.22),
    noise_region = c(-0.5, -2.5),
    optimal_smooth_criterion = "maic",
    aic_smoothing_factor = 5,
    anal_jac = TRUE,
    pre_fit_ppm_left = 4,
    pre_fit_ppm_right = 1.8,
    phi1_optim = FALSE,
    phi1_init = 0,
    max_dphi1 = 0.2,
    max_basis_shift_broad = 0.0078,
    max_basis_damping_broad = 2,
    ahat_calc_method = "lh_pnnls",
    prefit_phase_search = TRUE,
    freq_reg = NULL,
    output_all_paras = FALSE
)

```

Arguments

init_damping	initial value of the Gaussian global damping parameter (Hz). Very poorly shimmed or high field data may benefit from a larger value.
maxiters	The maximum number of iterations to run for the detailed fit.
max_shift	The maximum allowable shift to be applied in the optimisation phase of fitting (ppm).
max_damping	maximum permitted value of the global damping parameter (Hz).
max_phase	the maximum absolute permitted value of the global zero-order phase term (degrees). Note, the prefit_phase_search option is not constrained by this term.
lambda	manually set the the baseline smoothness parameter.
ppm_left	downfield frequency limit for the fitting range (ppm).

ppm_right	upfield frequency limit for the fitting range (ppm).
zp	zero pad the data to twice the original length before fitting.
bl_ed_pppm	manually set the the baseline smoothness parameter (ED per ppm).
auto_bl_flex	automatically determine the level of baseline smoothness.
bl_comps_pppm	spline basis density (signals per ppm).
export_sp_fit	add the fitted spline functions to the fit result.
max_asym	maximum allowable value of the asymmetry parameter.
max_basis_shift	maximum allowable frequency shift for individual basis signals (ppm).
max_basis_damping	maximum allowable Lorentzian damping factor for individual basis signals (Hz).
maxiters_pre	maximum iterations for the coarse (pre-)fit.
algo_pre	optimisation method for the coarse (pre-)fit.
min_bl_ed_pppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
max_bl_ed_pppm	minimum value for the candidate baseline flexibility analyses (ED per ppm).
auto_bl_flex_n	number of candidate baseline analyses to perform.
pre_fit_bl_ed_pppm	level of baseline flexibility to use in the coarse fitting stage of the algorithm (ED per ppm).
remove_lip_mm_prefit	remove broad signals in the coarse fitting stage of the algorithm.
pre_align	perform a pre-alignment step before coarse fitting.
max_pre_align_shift	maximum allowable shift in the pre-alignment step (ppm).
pre_align_ref_freqs	a vector of prominent spectral frequencies used in the pre-alignment step (ppm).
noise_region	spectral region to estimate the noise level (ppm).
optimal_smooth_criterion	method to determine the optimal smoothness.
aic_smoothing_factor	modification factor for the AIC calculation.
anal_jac	use a analytical approximation to the jacobian in the detailed fitting stage.
pre_fit_ppm_left	downfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
pre_fit_ppm_right	upfield frequency limit for the fitting range in the coarse fitting stage of the algorithm (ppm).
phi1_optim	apply and optimise a frequency dependant phase term.
phi1_init	initial value for the frequency dependant phase term (ms).

max_dphi1	maximum allowable change from the initial frequency dependant phase term (ms).
max_basis_shift_broad	maximum allowable shift for broad signals in the basis (ppm). Determined based on their name beginning with Lip or MM.
max_basis_damping_broad	maximum allowable Lorentzian damping for broad signals in the basis (Hz). Determined based on their name beginning with Lip or MM.
ahat_calc_method	method to calculate the metabolite amplitudes. May be one of: "lh_pnnls" or "ls".
prefit_phase_search	perform a 1D search for the optimal phase in the prefit stage of the algorithm.
freq_reg	frequency shift parameter.
output_allparas	include more fitting parameters in the fit table, e.g. individual shift and damping factors for each basis set element.

Value

full list of options.

Examples

```
opts <- abfit_opts(ppm_left = 4.2, noise_region = c(-1, -3))
```

abfit_opts_v1_9_0	<i>Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.</i>
-------------------	--

Description

Return a list of options for an ABfit analysis to maintain comparability with analyses performed with version 1.9.0 (and earlier) of spant.

Usage

```
abfit_opts_v1_9_0(...)
```

Arguments

... arguments passed to `abfit_opts`.

Value

full list of options.

acquire	<i>Simulate pulse sequence acquisition.</i>
---------	---

Description

Simulate pulse sequence acquisition.

Usage

```
acquire(sys, rec_phase = 180, tol = 1e-04, detect = NULL)
```

Arguments

sys	spin system object.
rec_phase	receiver phase in degrees.
tol	ignore resonance amplitudes below this threshold.
detect	detection nuclei.

Value

a list of resonance amplitudes and frequencies.

add_noise	<i>Add noise to an mrs_data object.</i>
-----------	---

Description

Add noise to an mrs_data object.

Usage

```
add_noise(mrs_data, sd = 0.1, fd = TRUE)
```

Arguments

mrs_data	data to add noise to.
sd	standard deviation of the noise.
fd	generate the noise samples in the frequency-domain (TRUE) or time-domain (FALSE). This is required since the absolute value of the standard deviation of noise samples changes when data is Fourier transformed.

Value

mrs_data object with additive normally distributed noise.

align	<i>Align spectra to a reference frequency using a convolution based method.</i>
-------	---

Description

Align spectra to a reference frequency using a convolution based method.

Usage

```
align(  
  mrs_data,  
  ref_freq = 4.65,  
  zf_factor = 2,  
  lb = 2,  
  max_shift = 20,  
  ret_df = FALSE,  
  mean_dyns = FALSE  
)
```

Arguments

mrs_data	data to be aligned.
ref_freq	reference frequency in ppm units. More than one frequency may be specified.
zf_factor	zero filling factor to increase alignment resolution.
lb	line broadening to apply to the reference signal.
max_shift	maximum allowable shift in Hz.
ret_df	return frequency shifts in addition to aligned data (logical).
mean_dyns	align the mean spectrum and apply the same shift to each dynamic.

Value

aligned data object.

apodise_xy	<i>Apodise MRSI data in the x-y direction with a k-space filter.</i>
------------	--

Description

Apodise MRSI data in the x-y direction with a k-space filter.

Usage

```
apodise_xy(mrs_data, func = "hamming", w = 2.5)
```

Arguments

mrs_data	MRSI data.
func	must be "hamming" or "gaussian".
w	the reciprocal of the standard deviation for the Gaussian function.

Value

apodised data.

append_basis	<i>Combine a pair of basis set objects.</i>
--------------	---

Description

Combine a pair of basis set objects.

Usage

```
append_basis(basis_a, basis_b)
```

Arguments

basis_a	first basis.
basis_b	second basis.

Value

combined basis set object.

append_coils	<i>Append MRS data across the coil dimension, assumes they matched across the other dimensions.</i>
--------------	---

Description

Append MRS data across the coil dimension, assumes they matched across the other dimensions.

Usage

```
append_coils(...)
```

Arguments

...	MRS data objects as arguments, or a list of MRS data objects.
-----	---

Value

a single MRS data object with the input objects concatenated together.

append_dyns	<i>Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.</i>
-------------	--

Description

Append MRS data across the dynamic dimension, assumes they matched across the other dimensions.

Usage

```
append_dyns(...)
```

Arguments

... MRS data objects as arguments, or a list of MRS data objects.

Value

a single MRS data object with the input objects concatenated together.

apply_axes	<i>Apply a function over specified array axes.</i>
------------	--

Description

Apply a function over specified array axes.

Usage

```
apply_axes(x, axes, fun, ...)
```

Arguments

x an array.
axes a vector of axes to apply fun over.
fun function to be applied.
... optional arguments to fun.

Value

array.

Examples

```
z <- array(1:1000, dim = c(10, 10, 10))
a <- apply_axes(z, 3, fft)
a[1,1,] == fft(z[1,1,])
a <- apply_axes(z, 3, sum)
a[1,1,] == sum(z[1,1,])
```

apply_mrs*Apply a function across given dimensions of a MRS data object.*

Description

Apply a function across given dimensions of a MRS data object.

Usage

```
apply_mrs(mrs_data, dims, fun, ..., data_only = FALSE)
```

Arguments

<code>mrs_data</code>	MRS data.
<code>dims</code>	dimensions to apply the function.
<code>fun</code>	name of the function.
<code>...</code>	arguments to the function.
<code>data_only</code>	return an array rather than an MRS data object.

apply_pvc*Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.*

Description

Convert default LCM/TARQUIN concentration scaling to molal units with partial volume correction.

Usage

```
apply_pvc(fit_result, p_vols, te, tr)
```

Arguments

<code>fit_result</code>	a <code>fit_result</code> object to apply partial volume correction.
<code>p_vols</code>	a numeric vector of partial volumes.
<code>te</code>	the MRS TE.
<code>tr</code>	the MRS TR.

Value

a `fit_result` object with a rescaled results table.

Arg.mrs_data	<i>Apply Arg operator to an MRS dataset.</i>
--------------	--

Description

Apply Arg operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Arg(z)
```

Arguments

`z` MRS data.

Value

MRS data following Arg operator.

array2mrs_data	<i>Convert a 7 dimensional array in into a mrs_data object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.</i>
----------------	---

Description

Convert a 7 dimensional array in into a `mrs_data` object. The array dimensions should be ordered as : dummy, X, Y, Z, dynamic, coil, FID.

Usage

```
array2mrs_data(
  data_array,
  fs = def_fs(),
  ft = def_ft(),
  ref = def_ref(),
  nuc = def_nuc(),
  fd = FALSE
)
```

Arguments

data_array	7d data array.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	nucleus that is resonant at the transmitter frequency.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

auto_phase	<i>Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.</i>
------------	---

Description

Perform zeroth-order phase correction based on the minimisation of the squared difference between the real and magnitude components of the spectrum.

Usage

```
auto_phase(mrs_data, xlim = NULL, ret_phase = FALSE)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to including in the phase.
ret_phase	return phase values (logical).

Value

MRS data object and phase values (optional).

back_extrap_ar	<i>Back extrapolate time-domain data points using an autoregressive model.</i>
----------------	--

Description

Back extrapolate time-domain data points using an autoregressive model.

Usage

```
back_extrap_ar(
  mrs_data,
  extrap_pts,
  pred_pts = NULL,
  method = "burg",
  rem_add = TRUE,
  ...
)
```

Arguments

mrs_data	mrs_data object.
extrap_pts	number of points to extrapolate.
pred_pts	number of points to base the extrapolation on.
method	character string specifying the method to fit the model. Must be one of the strings in the default argument (the first few characters are sufficient). Defaults to "burg".
rem_add	remove additional points from the end of the FID to maintain the original length of the dataset. Default to TRUE.
...	additional arguments to specific methods, see ?ar.

Value

back extrapolated data.

basis2mrs_data	<i>Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.</i>
----------------	--

Description

Convert a basis object to an mrs_data object - where basis signals are spread across the dynamic dimension.

Usage

```
basis2mrs_data(basis, sum_elements = FALSE, amps = NULL, shifts = NULL)
```

Arguments

basis	basis set object.
sum_elements	return the sum of basis elements (logical)
amps	a vector of scaling factors to apply to each basis element.
shifts	a vector of frequency shifts (in ppm) to apply to each basis element.

Value

an mrs_data object with basis signals spread across the dynamic dimension or summed.

bbase	<i>Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.</i>
-------	---

Description

Generate a spline basis, slightly adapted from : "Splines, knots, and penalties", Eilers 2010.

Usage

```
bbase(N, number, deg = 3)
```

Arguments

N	number of data points.
number	number of spline functions.
deg	spline degree : deg = 1 linear, deg = 2 quadratic, deg = 3 cubic.

Value

spline basis as a matrix.

bc_als	<i>Baseline correction using the ALS method.</i>
--------	--

Description

Baseline correction using the ALS method.

Usage

```
bc_als(mrs_data, lambda = 10000, p = 0.001)
```

Arguments

mrs_data	mrs_data object.
lambda	lambda parameter.
p	p parameter.

Value

baseline corrected data.

bc_constant	<i>Remove a constant baseline offset based on a reference spectral region.</i>
-------------	--

Description

Remove a constant baseline offset based on a reference spectral region.

Usage

```
bc_constant(mrs_data, xlim = NULL)
```

Arguments

mrs_data	MRS data.
xlim	spectral range containing a flat baseline region to measure the offset.

Value

baseline corrected data.

beta2lw	<i>Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.</i>
---------	--

Description

Covert a beta value in the time-domain to an equivalent linewidth in Hz: $x * \exp(-i * t * t * \text{beta})$.

Usage

```
beta2lw(beta)
```

Arguments

beta beta damping value.

Value

linewidth value in Hz.

calc_coil_noise_cor	<i>Calculate the noise correlation between coil elements.</i>
---------------------	---

Description

Calculate the noise correlation between coil elements.

Usage

```
calc_coil_noise_cor(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

correlation matrix.

calc_coil_noise_sd *Calculate the noise standard deviation for each coil element.*

Description

Calculate the noise standard deviation for each coil element.

Usage

```
calc_coil_noise_sd(noise_data)
```

Arguments

noise_data mrs_data object with one FID for each coil element.

Value

array of standard deviations.

calc_ed_from_lambda *Calculate the effective dimensions of a spline smoother from lambda.*

Description

Calculate the effective dimensions of a spline smoother from lambda.

Usage

```
calc_ed_from_lambda(spline_basis, deriv_mat, lambda)
```

Arguments

spline_basis spline basis.
deriv_mat derivative matrix.
lambda smoothing parameter.

Value

the effective dimension value.

calc_peak_info_vec *Calculate the FWHM of a peak from a vector of intensity values.*

Description

Calculate the FWHM of a peak from a vector of intensity values.

Usage

```
calc_peak_info_vec(data_pts, interp_f)
```

Arguments

data_pts input vector.
interp_f interpolation factor to improve the FWHM estimate.

Value

a vector of: x position of the highest data point, maximum peak value in the y axis, FWHM in the units of data points.

calc_sd_poly *Perform a polynomial fit, subtract and return the standard deviation of the residuals.*

Description

Perform a polynomial fit, subtract and return the standard deviation of the residuals.

Usage

```
calc_sd_poly(y, degree = 1)
```

Arguments

y array.
degree polynomial degree.

Value

standard deviation of the fit residuals.

calc_spec_diff	<i>Calculate the sum of squares differences between two mrs_data objects.</i>
----------------	---

Description

Calculate the sum of squares differences between two mrs_data objects.

Usage

```
calc_spec_diff(mrs_data, ref = NULL, xlim = c(4, 0.5))
```

Arguments

mrs_data	mrs_data object.
ref	reference mrs_data object to calculate differences.
xlim	spectral limits to perform calculation.

Value

an array of the sum of squared difference values.

calc_spec_snr	<i>Calculate the spectral SNR.</i>
---------------	------------------------------------

Description

SNR is defined as the maximum signal value divided by the standard deviation of the noise.

Usage

```
calc_spec_snr(  
  mrs_data,  
  sig_region = c(4, 0.5),  
  noise_region = c(-0.5, -2.5),  
  p_order = 2,  
  interp_f = 4,  
  full_output = FALSE  
)
```

Arguments

mrs_data	an object of class mrs_data.
sig_region	a ppm region to define where the maximum signal value should be estimated.
noise_region	a ppm region to defined where the noise level should be estimated.
p_order	polynomial order to fit to the noise region before estimating the standard deviation.
interp_f	interpolation factor to improve detection of the highest signal value.
full_output	output signal, noise and SNR values separately.

Details

The mean noise value is subtracted from the maximum signal value to reduce DC offset bias. A polynomial detrending fit (second order by default) is applied to the noise region before the noise standard deviation is estimated.

Value

an array of SNR values.

check_lcm	<i>Check LCMModel can be run</i>
-----------	----------------------------------

Description

Check LCMModel can be run

Usage

check_lcm()

check_tqn	<i>Check the TARQUIN binary can be run</i>
-----------	--

Description

Check the TARQUIN binary can be run

Usage

check_tqn()

circ_mask	<i>Create a logical circular mask spanning the full extent of an n x n matrix.</i>
-----------	--

Description

Create a logical circular mask spanning the full extent of an n x n matrix.

Usage

```
circ_mask(d, n, offset = 1)
```

Arguments

d	diameter of the mask.
n	number of matrix rows and columns.
offset	offset the mask centre in matrix dimension units.

Value

logical n x n mask matrix.

collapse_to_dyns	<i>Collapse MRS data by concatenating spectra along the dynamic dimension.</i>
------------------	--

Description

Collapse MRS data by concatenating spectra along the dynamic dimension.

Usage

```
collapse_to_dyns(x, rm_masked = FALSE)
```

```
## S3 method for class 'mrs_data'  
collapse_to_dyns(x, rm_masked = FALSE)
```

```
## S3 method for class 'fit_result'  
collapse_to_dyns(x, rm_masked = FALSE)
```

Arguments

x	data object to be collapsed (mrs_data or fit_result object).
rm_masked	remove masked dynamics from the output.

Value

collapsed data with spectra or fits concatenated along the dynamic dimension.

comb_coils	<i>Combine coil data based on the first data point of a reference signal.</i>
------------	---

Description

By default, elements are phased and scaled prior to summation. Where a reference signal is not given, the mean dynamic signal will be used instead.

Usage

```
comb_coils(
  metab,
  ref = NULL,
  noise = NULL,
  scale = TRUE,
  scale_method = "sig_noise_sq",
  sum_coils = TRUE,
  noise_region = c(-0.5, -2.5),
  average_ref_dyns = TRUE,
  ref_pt_index = 1
)
```

Arguments

metab	MRS data containing metabolite data.
ref	MRS data containing reference data (optional).
noise	MRS data from a noise scan (optional).
scale	option to rescale coil elements based on the first data point (logical).
scale_method	one of "sig_noise_sq", "sig_noise" or "sig".
sum_coils	sum the coil elements as a final step (logical).
noise_region	the spectral region (in ppm) to estimate the noise.
average_ref_dyns	take the mean of the reference scans in the dynamic dimension before use.
ref_pt_index	time-domain point to use for estimating phase and scaling values.

Value

MRS data.

`comb_fit_list_fit_tables`

Combine all fitting data points from a list of fits into a single data frame.

Description

Combine all fitting data points from a list of fits into a single data frame.

Usage

```
comb_fit_list_fit_tables(  
  fit_list,  
  add_extra = TRUE,  
  harmonise_ppm = TRUE,  
  inc_basis_sigs = FALSE,  
  inc_indices = TRUE,  
  add_res_id = TRUE  
)
```

Arguments

<code>fit_list</code>	list of <code>fit_result</code> objects.
<code>add_extra</code>	add variables in the extra data frame to the output (TRUE).
<code>harmonise_ppm</code>	ensure the ppm scale for each fit is identical to the first.
<code>inc_basis_sigs</code>	include the individual fitting basis signals in the output table, defaults to FALSE.
<code>inc_indices</code>	include indices such as X, Y and coil in the output, defaults to TRUE. These are generally not useful for SVS analysis.
<code>add_res_id</code>	add a <code>res_id</code> column to the output to distinguish between datasets.

Value

a data frame containing the fit data points.

`comb_fit_list_result_tables`

Combine the fit result tables from a list of fit results.

Description

Combine the fit result tables from a list of fit results.

Usage

```
comb_fit_list_result_tables(fit_list, add_extra = TRUE, add_res_id = TRUE)
```

Arguments

fit_list	a list of fit_result objects.
add_extra	add variables in the extra data frame to the output (TRUE).
add_res_id	add a res_id column to the output to distinguish between datasets.

Value

a data frame combine all fit result tables with an additional id column to differentiate between data sets. Any variables in the extra data frame may be optionally added to the result.

comb_fit_tables	<i>Combine all fitting data points into a single data frame.</i>
-----------------	--

Description

Combine all fitting data points into a single data frame.

Usage

```
comb_fit_tables(fit_res, inc_basis_sigs = FALSE, inc_indices = TRUE)
```

Arguments

fit_res	a single fit_result object.
inc_basis_sigs	include the individual fitting basis signals in the output table, defaults to FALSE.
inc_indices	include indices such as X, Y and coil in the output, defaults to TRUE. These are generally not useful for SVS analysis.

Value

a data frame containing the fit data points.

comb_metab_ref	<i>Combine a reference and metabolite mrs_data object.</i>
----------------	--

Description

Combine a reference and metabolite mrs_data object.

Usage

```
comb_metab_ref(metab, ref)
```

Arguments

metab	metabolite mrs_data object.
ref	reference mrs_data object.

Value

combined metabolite and reference mrs_data object.

Conj.mrs_data	<i>Apply Conj operator to an MRS dataset.</i>
---------------	---

Description

Apply Conj operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Conj(z)
```

Arguments

z	MRS data.
---	-----------

Value

MRS data following Conj operator.

conv_mrs	<i>Convolve two MRS data objects.</i>
----------	---------------------------------------

Description

Convolve two MRS data objects.

Usage

```
conv_mrs(mrs_data, conv)
```

Arguments

mrs_data	MRS data to be convolved.
conv	convolution data stored as an mrs_data object.

Value

convolved data.

crop_spec	<i>Crop mrs_data object based on a frequency range.</i>
-----------	---

Description

Crop mrs_data object based on a frequency range.

Usage

```
crop_spec(mrs_data, xlim = c(4, 0.2), scale = "ppm")
```

Arguments

mrs_data	MRS data.
xlim	range of values to crop in the spectral dimension eg xlim = c(4, 0.2).
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".

Value

cropped mrs_data object.

crop_td_pts	<i>Crop mrs_data object data points in the time-domain.</i>
-------------	---

Description

Crop mrs_data object data points in the time-domain.

Usage

```
crop_td_pts(mrs_data, start = NULL, end = NULL)
```

Arguments

mrs_data	MRS data.
start	starting data point (defaults to 1).
end	ending data point (defaults to the last saved point).

Value

cropped mrs_data object.

crop_xy	<i>Crop an MRSI dataset in the x-y direction</i>
---------	--

Description

Crop an MRSI dataset in the x-y direction

Usage

```
crop_xy(mrs_data, x_dim, y_dim)
```

Arguments

mrs_data	MRS data object.
x_dim	x dimension output length.
y_dim	y dimension output length.

Value

selected subset of MRS data.

crossprod_3d	<i>Compute the vector cross product between vectors x and y. Adapted from http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function</i>
--------------	---

Description

Compute the vector cross product between vectors x and y. Adapted from <http://stackoverflow.com/questions/15162741/what-is-rs-crossproduct-function>

Usage

```
crossprod_3d(x, y)
```

Arguments

x	vector of length 3.
y	vector of length 3.

Value

vector cross product of x and y.

decimate_mrs_fd	<i>Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.</i>
-----------------	--

Description

Decimate an MRS signal to half the original sampling frequency by filtering in the frequency domain before down sampling.

Usage

```
decimate_mrs_fd(mrs_data)
```

Arguments

mrs_data MRS data object.

Value

decimated data at half the original sampling frequency.

decimate_mrs_td	<i>Decimate an MRS signal by filtering in the time domain before down-sampling.</i>
-----------------	---

Description

Decimate an MRS signal by filtering in the time domain before downsampling.

Usage

```
decimate_mrs_td(mrs_data, q = 2, n = 4, ftype = "iir")
```

Arguments

mrs_data MRS data object.
q integer factor to downsample by (default = 2).
n filter order used in the downsampling.
ftype filter type, "iir" or "fir".

Value

decimated data.

def_acq_paras	<i>Return (and optionally modify using the input arguments) a list of the default acquisition parameters.</i>
---------------	---

Description

Return (and optionally modify using the input arguments) a list of the default acquisition parameters.

Usage

```
def_acq_paras(  
    ft = getOption("spant.def_ft"),  
    fs = getOption("spant.def_fs"),  
    N = getOption("spant.def_N"),  
    ref = getOption("spant.def_ref"),  
    nuc = getOption("spant.def_nuc")  
)
```

Arguments

ft	specify the transmitter frequency in Hz.
fs	specify the sampling frequency in Hz.
N	specify the number of data points in the spectral dimension.
ref	specify the reference value for ppm scale.
nuc	specify the resonant nucleus.

Value

A list containing the following elements:

- ft transmitter frequency in Hz.
- fs sampling frequency in Hz.
- N number of data points in the spectral dimension.
- ref reference value for ppm scale.
- nuc resonant nucleus.

def_fs	<i>Return the default sampling frequency in Hz.</i>
--------	---

Description

Return the default sampling frequency in Hz.

Usage

def_fs()

Value

sampling frequency in Hz.

def_ft	<i>Return the default transmitter frequency in Hz.</i>
--------	--

Description

Return the default transmitter frequency in Hz.

Usage

def_ft()

Value

transmitter frequency in Hz.

def_N	<i>Return the default number of data points in the spectral dimension.</i>
-------	--

Description

Return the default number of data points in the spectral dimension.

Usage

def_N()

Value

number of data points in the spectral dimension.

def_nuc	<i>Return the default nucleus.</i>
---------	------------------------------------

Description

Return the default nucleus.

Usage

```
def_nuc()
```

Value

number of data points in the spectral dimension.

def_ref	<i>Return the default reference value for ppm scale.</i>
---------	--

Description

Return the default reference value for ppm scale.

Usage

```
def_ref()
```

Value

reference value for ppm scale.

dicom_reader	<i>A very simple DICOM reader.</i>
--------------	------------------------------------

Description

Note this reader is very basic and does not use a DICOM dictionary or try to convert the data to the correct datatype. For a more robust and sophisticated reader use the oro.dicom package.

Usage

```
dicom_reader(  
    input,  
    tags = list(sop_class_uid = "0008,0016"),  
    endian = "little",  
    debug = FALSE  
)
```

Arguments

input	either a file path or raw binary object.
tags	a named list of tags to be extracted from the file. eg tags <- list(spec_data = "7FE1,1010", pat_name = "0010,0010")
endian	can be "little" or "big".
debug	print out some debugging information, can be "little" or "big".

Value

a list with the same structure as the input, but with tag codes replaced with the corresponding data in a raw format.

diff_mrs	<i>Apply the diff operator to an MRS dataset in the FID/spectral dimension.</i>
----------	---

Description

Apply the diff operator to an MRS dataset in the FID/spectral dimension.

Usage

```
diff_mrs(mrs_data, ...)
```

Arguments

mrs_data	MRS data.
...	additional arguments to the diff function.

Value

MRS data following diff operator.

downsample_mrs_fd	<i>Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.</i>
-------------------	--

Description

Downsample an MRS signal by a factor of 2 using an FFT "brick-wall" filter.

Usage

```
downsample_mrs_fd(mrs_data)
```

Arguments

mrs_data MRS data object.

Value

downsampled data.

downsample_mrs_td	<i>Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.</i>
-------------------	---

Description

Downsample an MRS signal by a factor of 2 by removing every other data point in the time-domain. Note, signals outside the new sampling frequency will be aliased.

Usage

```
downsample_mrs_td(mrs_data)
```

Arguments

mrs_data MRS data object.

Value

downsampled data.

`ecc` *Eddy current correction.*

Description

Apply eddy current correction using the Klose method.

Usage

```
ecc(metab, ref, rev = FALSE)
```

Arguments

<code>metab</code>	MRS data to be corrected.
<code>ref</code>	reference dataset.
<code>rev</code>	reverse the correction.

Details

In vivo proton spectroscopy in presence of eddy currents. Klose U. Magn Reson Med. 1990 Apr;14(1):26-30.

Value

corrected data in the time domain.

`elliptical_mask` *Create an elliptical mask stored as a matrix of logical values.*

Description

Create an elliptical mask stored as a matrix of logical values.

Usage

```
elliptical_mask(xN, yN, x0, y0, xr, yr, angle)
```

Arguments

<code>xN</code>	number of pixels in the x dimension.
<code>yN</code>	number of pixels in the y dimension.
<code>x0</code>	centre of ellipse in the x direction in units of pixels.
<code>y0</code>	centre of ellipse in the y direction in units of pixels.
<code>xr</code>	radius in the x direction in units of pixels.
<code>yr</code>	radius in the y direction in units of pixels.
<code>angle</code>	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

est_noise_sd	<i>Estimate the standard deviation of the noise from a segment of an mrs_data object.</i>
--------------	---

Description

Estimate the standard deviation of the noise from a segment of an mrs_data object.

Usage

```
est_noise_sd(mrs_data, n = 100, offset = 100, p_order = 2)
```

Arguments

mrs_data	MRS data object.
n	number of data points (taken from the end of array) to use in the estimation.
offset	number of final points to exclude from the calculation.
p_order	polynomial order to fit to the data before estimating the standard deviation.

Value

standard deviation array.

fd2td	<i>Transform frequency-domain data to the time-domain.</i>
-------	--

Description

Transform frequency-domain data to the time-domain.

Usage

```
fd2td(mrs_data)
```

Arguments

mrs_data	MRS data in frequency-domain representation.
----------	--

Value

MRS data in time-domain representation.

fd_conv_filt	<i>Frequency-domain convolution based filter.</i>
--------------	---

Description

Frequency-domain convolution based filter.

Usage

```
fd_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

fit_amps	<i>Extract the fit amplitudes from an object of class fit_result.</i>
----------	---

Description

Extract the fit amplitudes from an object of class fit_result.

Usage

```
fit_amps(
  x,
  inc_index = FALSE,
  sort_names = FALSE,
  append_common_1h_comb = TRUE
)
```

Arguments

x	fit_result object.
inc_index	include columns for the voxel index.
sort_names	sort the basis set names alphabetically.
append_common_1h_comb	append commonly used 1H metabolite combinations eg tNAA = NAA + NAAG.

Value

a dataframe of amplitudes.

fit_diags	<i>Calculate diagnostic information for object of class fit_result.</i>
-----------	---

Description

Calculate diagnostic information for object of class fit_result.

Usage

```
fit_diags(x, amps = NULL)
```

Arguments

x	fit_result object.
amps	known metabolite amplitudes.

Value

a dataframe of diagnostic information.

fit_mrs	<i>Perform a fit based analysis of MRS data.</i>
---------	--

Description

Note that TARQUIN and LCModel require these packages to be installed, and the functions set_tqn_cmd and set_lcm_cmd (respectively) need to be used to specify the location of these software packages.

Usage

```
fit_mrs(  
  metab,  
  basis = NULL,  
  method = "ABFIT",  
  w_ref = NULL,  
  opts = NULL,  
  parallel = FALSE,  
  time = TRUE,  
  progress = "text",  
  extra = NULL  
)
```

Arguments

metab	metabolite data.
basis	basis class object or character vector to basis file in LCModel .basis format.
method	'ABFIT' (default), 'VARPRO', 'VARPRO_3P', 'TARQUIN' or 'LCMODEL'.
w_ref	water reference data for concentration scaling (optional).
opts	options to pass to the analysis method.
parallel	perform analyses in parallel (TRUE or FALSE).
time	measure the time taken for the analysis to complete (TRUE or FALSE).
progress	option is passed to plyr::alply function to display a progress bar during fitting. Default value is "text", set to "none" to disable.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Details

Fitting approaches described in the following references: ABfit Wilson, M. Adaptive baseline fitting for 1H MR spectroscopy analysis. *Magn Reson Med* 2012;85:13-29.

VARPRO van der Veen JW, de Beer R, Luyten PR, van Ormondt D. Accurate quantification of in vivo 31P NMR signals using the variable projection method and prior knowledge. *Magn Reson Med* 1988;6:92-98.

TARQUIN Wilson, M., Reynolds, G., Kauppinen, R. A., Arvanitis, T. N. & Peet, A. C. A constrained least-squares approach to the automated quantitation of in vivo 1H magnetic resonance spectroscopy data. *Magn Reson Med* 2011;65:1-12.

LCModel Provencher SW. Estimation of metabolite concentrations from localized in vivo proton NMR spectra. *Magn Reson Med* 1993;30:672-679.

Value

MRS analysis object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package =
"spant")
svs <- read_mrs(fname)
## Not run:
basis <- sim_basis_1h_brain_press(svs)
fit_result <- fit_mrs(svs, basis)

## End(Not run)
```

fit_res2csv	<i>Write fit results table to a csv file.</i>
-------------	---

Description

Write fit results table to a csv file.

Usage

```
fit_res2csv(fit_res, fname, unscaled = FALSE)
```

Arguments

fit_res	fit result object.
fname	filename of csv file.
unscaled	output the unscaled result table (default = FALSE).

fp_phase	<i>Return the phase of the first data point in the time-domain.</i>
----------	---

Description

Return the phase of the first data point in the time-domain.

Usage

```
fp_phase(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

phase values in degrees.

fp_phase_correct	<i>Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.</i>
------------------	---

Description

Perform a zeroth order phase correction based on the phase of the first data point in the time-domain.

Usage

```
fp_phase_correct(mrs_data, ret_phase = FALSE)
```

Arguments

mrs_data	MRS data to be corrected.
ret_phase	return phase values (logical).

Value

corrected data or a list with corrected data and optional phase values.

fp_scale	<i>Scale the first time-domain data point in an mrs_data object.</i>
----------	--

Description

Scale the first time-domain data point in an mrs_data object.

Usage

```
fp_scale(mrs_data, scale = 0.5)
```

Arguments

mrs_data	MRS data.
scale	scaling value, defaults to 0.5.

Value

scaled mrs_data object.

fs	<i>Return the sampling frequency in Hz of an MRS dataset.</i>
----	---

Description

Return the sampling frequency in Hz of an MRS dataset.

Usage

```
fs(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

sampling frequency in Hz.

ft_dyns	<i>Apply the Fourier transform over the dynamic dimension.</i>
---------	--

Description

Apply the Fourier transform over the dynamic dimension.

Usage

```
ft_dyns(mrs_data, ft_shift = FALSE, ret_mod = FALSE, fd = TRUE)
```

Arguments

mrs_data	MRS data where the dynamic dimension is in the time-domain.
ft_shift	apply FT shift to the output, default is FALSE.
ret_mod	return the modulus out the transform, default is FALSE.
fd	transform the chemical shift axis to the frequency domain first, default is TRUE.

Value

transformed MRS data.

ft_shift	<i>Perform a fft and fshift on a vector.</i>
----------	--

Description

Perform a fft and fshift on a vector.

Usage

```
ft_shift(vec_in)
```

Arguments

vec_in vector input.

Value

output vector.

ft_shift_mat	<i>Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.</i>
--------------	---

Description

Perform a fft and fftshift on a matrix with each column replaced by its shifted fft.

Usage

```
ft_shift_mat(mat_in)
```

Arguments

mat_in matrix input.

Value

output matrix.

gausswin_2d	<i>Create a two dimensional Gaussian window function stored as a matrix.</i>
-------------	--

Description

Create a two dimensional Gaussian window function stored as a matrix.

Usage

```
gausswin_2d(xN, yN, x0, y0, xw, yw)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of window function in the x direction in units of pixels. Note, only integer values are applied.
y0	centre of window function in the y direction in units of pixels. Note, only integer values are applied.
xw	the reciprocal of the standard deviation of the Gaussian window in x direction.
yw	the reciprocal of the standard deviation of the Gaussian window in y direction.

Value

matrix with dimensions fov_yN x fov_xN.

gen_F	<i>Generate the F product operator.</i>
-------	---

Description

Generate the F product operator.

Usage

```
gen_F(sys, op, detect = NULL)
```

Arguments

sys	spin system object.
op	operator, one of "x", "y", "z", "p", "m".
detect	detection nuclei.

Value

F product operator matrix.

gen_F_xy

Generate the Fxy product operator with a specified phase.

Description

Generate the Fxy product operator with a specified phase.

Usage

```
gen_F_xy(sys, phase, detect = NULL)
```

Arguments

sys	spin system object.
phase	phase angle in degrees.
detect	detection nuclei.

Value

product operator matrix.

get_1h_brain_basis_paras

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v1

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

get_1h_brain_basis_paras_v1(ft, metab_lw = NULL, lcm_compat = FALSE)

Arguments

ft transmitter frequency in Hz.
metab_lw linewidth of metabolite signals (Hz).
lcm_compat when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v2

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

get_1h_brain_basis_paras_v2(ft, metab_lw = NULL, lcm_compat = FALSE)

Arguments

ft transmitter frequency in Hz.
metab_lw linewidth of metabolite signals (Hz).
lcm_compat when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_1h_brain_basis_paras_v3

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Description

Return a list of mol_parameter objects suitable for 1H brain MRS analyses.

Usage

```
get_1h_brain_basis_paras_v3(ft, metab_lw = NULL, lcm_compat = FALSE)
```

Arguments

ft	transmitter frequency in Hz.
metab_lw	linewidth of metabolite signals (Hz).
lcm_compat	when TRUE, lipid, MM and -CrCH molecules will be excluded from the output.

Value

list of mol_parameter objects.

get_2d_psf

Get the point spread function (PSF) for a 2D phase encoded MRSI scan.

Description

Get the point spread function (PSF) for a 2D phase encoded MRSI scan.

Usage

```
get_2d_psf(FOV = 160, mat_size = 16, sampling = "circ", hamming = FALSE)
```

Arguments

FOV	field of view in mm.
mat_size	acquisition matrix size (not interpolated).
sampling	can be either "circ" for circular or "rect" for rectangular.
hamming	should Hamming k-space weighting be applied (default FALSE).

Value

A matrix of the PSF with 1mm resolution.

get_acq_paras	<i>Return acquisition parameters from a MRS data object.</i>
---------------	--

Description

Return acquisition parameters from a MRS data object.

Usage

```
get_acq_paras(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

list of acquisition parameters.

get_dyns	<i>Extract a subset of dynamic scans.</i>
----------	---

Description

Extract a subset of dynamic scans.

Usage

```
get_dyns(mrs_data, subset)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be returned.

Value

MRS data containing the subset of requested dynamics.

get_even_dyns	<i>Return even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Return even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
get_even_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data containing even numbered scans.

get_fh_dyns	<i>Return the first half of a dynamic series.</i>
-------------	---

Description

Return the first half of a dynamic series.

Usage

```
get_fh_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

first half of the dynamic series.

get_fit_map	<i>Get a data array from a fit result.</i>
-------------	--

Description

Get a data array from a fit result.

Usage

```
get_fit_map(fit_res, name)
```

Arguments

fit_res	fit_result object.
name	name of the quantity to plot, eg "tNAA".

get_fp	<i>Return the first time-domain data point.</i>
--------	---

Description

Return the first time-domain data point.

Usage

```
get_fp(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

first time-domain data point.

get_guassian_pulse *Generate a gaussian pulse shape.*

Description

Generate a gaussian pulse shape.

Usage

```
get_guassian_pulse(angle, n, trunc = 1)
```

Arguments

angle	pulse angle in degrees.
n	number of points to generate.
trunc	percentage truncation factor.

get_head_dyns *Return the first scans of a dynamic series.*

Description

Return the first scans of a dynamic series.

Usage

```
get_head_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

first scans of a dynamic series.

get_lcm_cmd	<i>Print the command to run the LCModel command-line program.</i>
-------------	---

Description

Print the command to run the LCModel command-line program.

Usage

```
get_lcm_cmd()
```

get_metab	<i>Extract the metabolite component from an mrs_data object.</i>
-----------	--

Description

Extract the metabolite component from an mrs_data object.

Usage

```
get_metab(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

metabolite component.

get_mol_names	<i>Return a character array of names that may be used with the get_mol_paras function.</i>
---------------	--

Description

Return a character array of names that may be used with the get_mol_paras function.

Usage

```
get_mol_names()
```

Value

a character array of names.

get_mol_paras	<i>Get a mol_parameters object for a named molecule.</i>
---------------	--

Description

Get a mol_parameters object for a named molecule.

Usage

```
get_mol_paras(name, ...)
```

Arguments

name	the name of the molecule.
...	arguments to pass to molecule definition function.

get_mrsi2d_seg	<i>Calculate the partial volume estimates for each voxel in a 2D MRSI dataset.</i>
----------------	--

Description

Localisation is assumed to be perfect in the z direction and determined by the ker input in the x-y direction.

Usage

```
get_mrsi2d_seg(mrs_data, mri_seg, ker)
```

Arguments

mrs_data	2D MRSI data with multiple voxels in the x-y dimension.
mri_seg	MRI data with values corresponding to the segmentation class. Must be 1mm isotropic resolution.
ker	MRSI PSF kernel in the x-y direction compatible with the mmand package, eg: mmand::shapeKernel(c(10, 10), type = "box").

Value

a data frame of partial volume estimates and individual segmentation maps.

get_mrsi_voi *Generate a MRSI VOI from an mrs_data object.*

Description

Generate a MRSI VOI from an mrs_data object.

Usage

```
get_mrsi_voi(mrs_data, target_mri = NULL, map = NULL, ker = mmand::boxKernel())
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
map	optional voi intensity map.
ker	kernel to rescale the map data to the target_mri. Default value is mmand::boxKernel(), use mmand::mnKernel() for a smoothed map.

Value

volume data as a nifti object.

get_mrsi_voxel *Generate a MRSI voxel from an mrs_data object.*

Description

Generate a MRSI voxel from an mrs_data object.

Usage

```
get_mrsi_voxel(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrsi_voxel_xy_psf *Generate a MRSI voxel PSF from an mrs_data object.*

Description

Generate a MRSI voxel PSF from an mrs_data object.

Usage

```
get_mrsi_voxel_xy_psf(mrs_data, target_mri, x_pos, y_pos, z_pos)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.
x_pos	x voxel coordinate.
y_pos	y voxel coordinate.
z_pos	z voxel coordinate.

Value

volume data as a nifti object.

get_mrs_affine *Generate an affine for nifti generation.*

Description

Generate an affine for nifti generation.

Usage

```
get_mrs_affine(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1)
```

Arguments

mrs_data	input data.
x_pos	x_position coordinate.
y_pos	y_position coordinate.
z_pos	z_position coordinate.

Value

affine matrix.

get_odd_dyns	<i>Return odd numbered dynamic scans starting from 1 (1,3,5...).</i>
--------------	--

Description

Return odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
get_odd_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data containing odd numbered scans.

get_ref	<i>Extract the reference component from an mrs_data object.</i>
---------	---

Description

Extract the reference component from an mrs_data object.

Usage

```
get_ref(mrs_data)
```

Arguments

mrs_data MRS data.

Value

reference component.

get_seg_ind	<i>Get the indices of data points lying between two values (end > x > start).</i>
-------------	---

Description

Get the indices of data points lying between two values (end > x > start).

Usage

```
get_seg_ind(scale, start, end)
```

Arguments

scale	full list of values.
start	smallest value in the subset.
end	largest value in the subset.

Value

set of indices.

get_sh_dyns	<i>Return the second half of a dynamic series.</i>
-------------	--

Description

Return the second half of a dynamic series.

Usage

```
get_sh_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

second half of the dynamic series.

get_slice	<i>Return a single slice from a larger MRSI dataset.</i>
-----------	--

Description

Return a single slice from a larger MRSI dataset.

Usage

```
get_slice(mrs_data, z_pos)
```

Arguments

mrs_data	MRSI data.
z_pos	the z index to extract.

Value

MRS data.

get_subset	<i>Extract a subset of MRS data.</i>
------------	--------------------------------------

Description

Extract a subset of MRS data.

Usage

```
get_subset(  
  mrs_data,  
  x_set = NULL,  
  y_set = NULL,  
  z_set = NULL,  
  dyn_set = NULL,  
  coil_set = NULL,  
  fd_set = NULL,  
  td_set = NULL  
)
```

Arguments

mrs_data	MRS data object.
x_set	x indices to include in the output (default all).
y_set	y indices to include in the output (default all).
z_set	z indices to include in the output (default all).
dyn_set	dynamic indices to include in the output (default all).
coil_set	coil indices to include in the output (default all).
fd_set	frequency domain data indices to include in the output (default all).
td_set	time-domain indices to include in the output (default all).

Value

selected subset of MRS data.

get_svs_voi

Generate a SVS acquisition volume from an mrs_data object.

Description

Generate a SVS acquisition volume from an mrs_data object.

Usage

```
get_svs_voi(mrs_data, target_mri)
```

Arguments

mrs_data	MRS data.
target_mri	optional image data to match the intended volume space.

Value

volume data as a nifti object.

get_tail_dyns	<i>Return the last scans of a dynamic series.</i>
---------------	---

Description

Return the last scans of a dynamic series.

Usage

```
get_tail_dyns(mrs_data, n = 1)
```

Arguments

mrs_data	dynamic MRS data.
n	the number of dynamic scans to return.

Value

last scans of a dynamic series.

get_td_amp	<i>Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.</i>
------------	--

Description

Return an array of amplitudes derived from fitting the initial points in the time domain and extrapolating back to t=0.

Usage

```
get_td_amp(mrs_data, nstart = 10, nend = 50, method = "spline")
```

Arguments

mrs_data	MRS data.
nstart	first data point to fit.
nend	last data point to fit.
method	method for measuring the amplitude, one of "spline" or "exp".

Value

array of amplitudes.

get_tqn_cmd	<i>Print the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Print the command to run the TARQUIN command-line program.

Usage

```
get_tqn_cmd()
```

get_uncoupled_mol	<i>Generate a mol_parameters object for a simple spin system with one resonance.</i>
-------------------	--

Description

Generate a mol_parameters object for a simple spin system with one resonance.

Usage

```
get_uncoupled_mol(
    name,
    chem_shift,
    nucleus,
    scale_factor,
    lw,
    lg,
    full_name = NULL
)
```

Arguments

name	abbreviated name of the molecule.
chem_shift	chemical shift of the resonance (PPM).
nucleus	nucleus (1H, 31P...).
scale_factor	multiplicative scaling factor.
lw	linewidth in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
full_name	long name of the molecule (optional).

Value

mol_parameters object.

get_voi_cog	<i>Calculate the centre of gravity for an image containing 0 and 1's.</i>
-------------	---

Description

Calculate the centre of gravity for an image containing 0 and 1's.

Usage

```
get_voi_cog(voi)
```

Arguments

voi nifti object.

Value

triplet of x,y,z coordinates.

get_voi_seg	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg(voi, mri_seg)
```

Arguments

voi volume data as a nifti object.
mri_seg segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voi_seg_psf	<i>Return the white matter, gray matter and CSF composition of a volume.</i>
-----------------	--

Description

Return the white matter, gray matter and CSF composition of a volume.

Usage

```
get_voi_seg_psf(psf, mri_seg)
```

Arguments

psf	volume data as a nifti object.
mri_seg	segmented brain volume as a nifti object.

Value

a vector of partial volumes expressed as percentages.

get_voxel	<i>Return a single voxel from a larger mrs dataset.</i>
-----------	---

Description

Return a single voxel from a larger mrs dataset.

Usage

```
get_voxel(mrs_data, x_pos = 1, y_pos = 1, z_pos = 1, dyn = 1, coil = 1)
```

Arguments

mrs_data	MRS data.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.

Value

MRS data.

gridplot	<i>Arrange spectral plots in a grid.</i>
----------	--

Description

Arrange spectral plots in a grid.

Usage

```
gridplot(x, ...)
```

Arguments

x	object for plotting.
...	arguments to be passed to methods.

gridplot.mrs_data	<i>Arrange spectral plots in a grid.</i>
-------------------	--

Description

Arrange spectral plots in a grid.

Usage

```
## S3 method for class 'mrs_data'  
gridplot(  
  x,  
  rows = NA,  
  cols = NA,  
  mar = c(0, 0, 0, 0),  
  oma = c(3.5, 1, 1, 1),  
  bty = "o",  
  restore_def_par = TRUE,  
  ...  
)
```

Arguments

x	object of class mrs_data.
rows	number of grid rows.
cols	number of grid columns.
mar	option to adjust the plot margins. See ?par.
oma	outer margin area.

`bty` option to draw a box around the plot. See `?par`.
`restore_def_par` restore default plotting par values after the plot has been made.
`...` other arguments to pass to the plot method.

`grid_shift_xy` *Grid shift MRSI data in the x/y dimension.*

Description

Grid shift MRSI data in the x/y dimension.

Usage

```
grid_shift_xy(mrs_data, x_shift, y_shift)
```

Arguments

`mrs_data` MRSI data in the spatial domain.
`x_shift` shift to apply in the x-direction in units of voxels.
`y_shift` shift to apply in the y-direction in units of voxels.

Value

shifted data.

`hsvd` *HSVD of an mrs_data object.*

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. *J Magn Reson* 1987;73:553-557.

Usage

```
hsvd(mrs_data, comps = 40, irlba = TRUE, max_damp = 10)
```

Arguments

`mrs_data` `mrs_data` object to be decomposed.
`comps` number of Lorentzian components to use for modelling.
`irlba` option to use irlba SVD (logical).
`max_damp` maximum allowable damping factor.

Value

basis matrix and signal table.

hsvd_filt	<i>HSVD based signal filter.</i>
-----------	----------------------------------

Description

HSVD based signal filter described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_filt(
  mrs_data,
  xlim = c(-30, 30),
  comps = 40,
  irlba = TRUE,
  max_damp = 10,
  scale = "hz",
  return_model = FALSE
)
```

Arguments

mrs_data	MRS data to be filtered.
xlim	frequency range to filter, default units are Hz which can be changed to ppm using the "scale" argument.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor.
scale	either "hz" or "ppm" to set the frequency units of xlim.
return_model	by default the filtered spectrum is returned. Set return_model to TRUE to return the HSVD model of the data.

Value

filtered data or model depending on the return_model argument.

hsvd_vec	<i>HSVD of a complex vector.</i>
----------	----------------------------------

Description

HSVD method as described in: Barkhuijsen H, de Beer R, van Ormondt D. Improved algorithm for noniterative and timedomain model fitting to exponentially damped magnetic resonance signals. J Magn Reson 1987;73:553-557.

Usage

```
hsvd_vec(y, fs, comps = 40, irlba = TRUE, max_damp = 0)
```

Arguments

y	time domain signal to be filtered as a vector.
fs	sampling frequency of y.
comps	number of Lorentzian components to use for modelling.
irlba	option to use irlba SVD (logical).
max_damp	maximum allowable damping factor. Default value of 0 ensures resultant model is damped.

Value

basis matrix and signal table.

hz	<i>Return the frequency scale of an MRS dataset in Hz.</i>
----	--

Description

Return the frequency scale of an MRS dataset in Hz.

Usage

```
hz(mrs_data, fs = NULL, N = NULL)
```

Arguments

mrs_data	MRS data.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.

Value

frequency scale.

ift_shift	<i>Perform an iffshift and ifft on a vector.</i>
-----------	--

Description

Perform an iffshift and ifft on a vector.

Usage

```
ift_shift(vec_in)
```

Arguments

vec_in vector input.

Value

output vector.

ift_shift_mat	<i>Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.</i>
---------------	---

Description

Perform an ifft and ifftshift on a matrix with each column replaced by its shifted ifft.

Usage

```
ift_shift_mat(mat_in)
```

Arguments

mat_in matrix input.

Value

output matrix.

Im.mrs_data	<i>Apply Im operator to an MRS dataset.</i>
-------------	---

Description

Apply Im operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Im(z)
```

Arguments

z MRS data.

Value

MRS data following Im operator.

image.mrs_data	<i>Image plot method for objects of class mrs_data.</i>
----------------	---

Description

Image plot method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
image(
  x,
  xlim = NULL,
  mode = "re",
  col = NULL,
  plot_dim = NULL,
  x_pos = NULL,
  y_pos = NULL,
  z_pos = NULL,
  dyn = 1,
  coil = 1,
  restore_def_par = TRUE,
  y_ticks = NULL,
  vline = NULL,
  hline = NULL,
  ...
)
```

Arguments

x	object of class <code>mrs_data</code> .
xlim	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
col	Colour map to use, defaults to <code>viridis</code> .
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "x", "y", "z", "coil" or NULL. If NULL (the default) all spectra will be collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
restore_def_par	restore default plotting par values after the plot has been made.
y_ticks	a vector of indices specifying where to place tick marks.
vline	draw a vertical line at the value of <code>vline</code> .
hline	draw a horizontal line at the value of <code>hline</code> .
...	other arguments to pass to the plot method.

img2kspace_xy

Transform 2D MRSI data to k-space in the x-y direction.

Description

Transform 2D MRSI data to k-space in the x-y direction.

Usage

```
img2kspace_xy(mrs_data)
```

Arguments

mrs_data	2D MRSI data.
----------	---------------

Value

k-space data.

interleave_dyns	<i>Interleave the first and second half of a dynamic series.</i>
-----------------	--

Description

Interleave the first and second half of a dynamic series.

Usage

```
interleave_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

interleaved data.

int_spec	<i>Integrate a spectral region.</i>
----------	-------------------------------------

Description

See spec_op function for a more complete set of spectral operations.

Usage

```
int_spec(mrs_data, xlim = NULL, freq_scale = "ppm", mode = "re")
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

inv_even_dyns	<i>Invert even numbered dynamic scans starting from 1 (2,4,6...).</i>
---------------	---

Description

Invert even numbered dynamic scans starting from 1 (2,4,6...).

Usage

```
inv_even_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data with inverted even numbered scans.

inv_odd_dyns	<i>Invert odd numbered dynamic scans starting from 1 (1,3,5...).</i>
--------------	--

Description

Invert odd numbered dynamic scans starting from 1 (1,3,5...).

Usage

```
inv_odd_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

dynamic MRS data with inverted odd numbered scans.

`is.def`*Check if an object is defined, which is the same as being not NULL.*

Description

Check if an object is defined, which is the same as being not NULL.

Usage`is.def(x)`**Arguments**

`x` object to test for being NULL.

Value

logical value.

`is_fd`*Check if the chemical shift dimension of an MRS data object is in the frequency domain.*

Description

Check if the chemical shift dimension of an MRS data object is in the frequency domain.

Usage`is_fd(mrs_data)`**Arguments**

`mrs_data` MRS data.

Value

logical value.

kspace2img_xy	<i>Transform 2D MRSI data from k-space to image space in the x-y direction.</i>
---------------	---

Description

Transform 2D MRSI data from k-space to image space in the x-y direction.

Usage

```
kspace2img_xy(mrs_data)
```

Arguments

mrs_data 2D MRSI data.

Value

MRSI data in image space.

l2_reg	<i>Perform l2 regularisation artefact suppression.</i>
--------	--

Description

Perform l2 regularisation artefact suppression using the method proposed by Bilgic et al. JMRI 40(1):181-91 2014.

Usage

```
l2_reg(  
  mrs_data,  
  thresh = 0.05,  
  b = 1e-11,  
  A = NA,  
  xlim = NA,  
  thresh_xlim = NULL,  
  A_append = NULL,  
  ret_norms = FALSE  
)
```

Arguments

mrs_data	input data for artefact suppression.
thresh	threshold parameter to extract lipid signals from mrs_data based on the spectral integration of the thresh_xlim region in magnitude mode.
b	regularisation parameter.
A	set of spectra containing the artefact basis signals. The thresh parameter is ignored when A is specified.
xlim	spectral limits in ppm to restrict the reconstruction range. Defaults to the full spectral width.
thresh_xlim	spectral limits in ppm to integrate for the threshold map.
A_append	additional spectra to append to the A basis.
ret_norms	return the residual norm and solution norms.

Value

l2 reconstructed mrs_data object.

lb *Apply line-broadening (apodisation) to MRS data or basis object.*

Description

Apply line-broadening (apodisation) to MRS data or basis object.

Usage

```
lb(x, lb, lg = 1)

## S3 method for class 'list'
lb(x, lb, lg = 1)

## S3 method for class 'mrs_data'
lb(x, lb, lg = 1)

## S3 method for class 'basis_set'
lb(x, lb, lg = 1)
```

Arguments

x	input mrs_data or basis_set object.
lb	amount of line-broadening in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).

Value

line-broadened data.

lw2alpha	<i>Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.</i>
----------	---

Description

Covert a linewidth in Hz to an equivalent alpha value in the time-domain ie: $x * \exp(-t * \alpha)$.

Usage

lw2alpha(lw)

Arguments

lw linewidth in Hz.

Value

beta damping value.

lw2beta	<i>Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \beta)$.</i>
---------	---

Description

Covert a linewidth in Hz to an equivalent beta value in the time-domain ie: $x * \exp(-t * t * \beta)$.

Usage

lw2beta(lw)

Arguments

lw linewidth in Hz.

Value

beta damping value.

mask_dyns	<i>Mask an MRS dataset in the dynamic dimension.</i>
-----------	--

Description

Mask an MRS dataset in the dynamic dimension.

Usage

```
mask_dyns(mrs_data, mask)
```

Arguments

mrs_data	MRS data object.
mask	vector of boolean values specifying the dynamics to mask, where a value of TRUE indicates the spectrum should be removed.

Value

masked dataset.

mask_xy	<i>Mask an MRSI dataset in the x-y direction</i>
---------	--

Description

Mask an MRSI dataset in the x-y direction

Usage

```
mask_xy(mrs_data, x_dim, y_dim)
```

Arguments

mrs_data	MRS data object.
x_dim	x dimension output length.
y_dim	y dimension output length.

Value

masked MRS data.

mask_xy_mat	<i>Mask a 2D MRSI dataset in the x-y dimension.</i>
-------------	---

Description

Mask a 2D MRSI dataset in the x-y dimension.

Usage

```
mask_xy_mat(mrs_data, mask, value = NA)
```

Arguments

mrs_data	MRS data object.
mask	matrix of boolean values specifying the voxels to mask, where a value of TRUE indicates the voxel should be removed.
value	the value to set masked data to (usually NA or 0).

Value

masked dataset.

mat2mrs_data	<i>Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.</i>
--------------	---

Description

Convert a matrix (with spectral points in the column dimension and dynamics in the row dimensions) into a mrs_data object.

Usage

```
mat2mrs_data(
  mat,
  fs = def_fs(),
  ft = def_ft(),
  ref = def_ref(),
  nuc = def_nuc(),
  fd = FALSE
)
```

Arguments

mat	data matrix.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

max_mrs	<i>Apply the max operator to an MRS dataset.</i>
---------	--

Description

Apply the max operator to an MRS dataset.

Usage

```
max_mrs(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Value

MRS data following max operator.

max_mrs_interp	<i>Apply the max operator to an interpolated MRS dataset.</i>
----------------	---

Description

Apply the max operator to an interpolated MRS dataset.

Usage

```
max_mrs_interp(mrs_data, interp_f = 4)
```

Arguments

mrs_data MRS data.
 interp_f interpolation factor.

Value

Array of maximum values (real only).

mean.mrs_data	<i>Calculate the mean spectrum from an mrs_data object.</i>
---------------	---

Description

Calculate the mean spectrum from an mrs_data object.

Usage

```
## S3 method for class 'mrs_data'
mean(x, ...)
```

Arguments

x object of class mrs_data.
 ... other arguments to pass to the colMeans function.

Value

mean mrs_data object.

mean_dyns	<i>Calculate the mean dynamic data.</i>
-----------	---

Description

Calculate the mean dynamic data.

Usage

```
mean_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

mean dynamic data.

mean_dyn_blocks	<i>Calculate the mean of adjacent dynamic scans.</i>
-----------------	--

Description

Calculate the mean of adjacent dynamic scans.

Usage

```
mean_dyn_blocks(mrs_data, block_size)
```

Arguments

mrs_data	dynamic MRS data.
block_size	number of adjacent dynamics scans to average over.

Value

dynamic data averaged in blocks.

mean_dyn_pairs	<i>Calculate the pairwise means across a dynamic data set.</i>
----------------	--

Description

Calculate the pairwise means across a dynamic data set.

Usage

```
mean_dyn_pairs(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

mean dynamic data of adjacent dynamic pairs.

mean_mrs_list	<i>Return the mean of a list of mrs_data objects.</i>
---------------	---

Description

Return the mean of a list of mrs_data objects.

Usage

```
mean_mrs_list(mrs_list)
```

Arguments

mrs_list list of mrs_data objects.

Value

mean mrs_data object.

median_dyns	<i>Calculate the median dynamic data.</i>
-------------	---

Description

Calculate the median dynamic data.

Usage

```
median_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

median dynamic data.

Mod.mrs_data	<i>Apply Mod operator to an MRS dataset.</i>
--------------	--

Description

Apply Mod operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Mod(z)
```

Arguments

z MRS data.

Value

MRS data following Mod operator.

mrs_data2basis	<i>Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.</i>
----------------	--

Description

Convert an mrs_data object to basis object - where basis signals are spread across the dynamic dimension in the MRS data.

Usage

```
mrs_data2basis(mrs_data, names)
```

Arguments

mrs_data mrs_data object with basis signals spread across the dynamic dimension.
names list of names corresponding to basis signals.

Value

basis set object.

mrs_data2mat	<i>Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.</i>
--------------	---

Description

Convert mrs_data object to a matrix, with spectral points in the column dimension and dynamics in the row dimension.

Usage

```
mrs_data2mat(mrs_data, collapse = TRUE)
```

Arguments

mrs_data	MRS data object or list of MRS data objects.
collapse	collapse all other dimensions along the dynamic dimension, eg a 16x16 MRSI grid would be first collapsed across 256 dynamic scans.

Value

MRS data matrix.

mrs_data2vec	<i>Convert mrs_data object to a vector.</i>
--------------	---

Description

Convert mrs_data object to a vector.

Usage

```
mrs_data2vec(mrs_data, dyn = 1, x_pos = 1, y_pos = 1, z_pos = 1, coil = 1)
```

Arguments

mrs_data	MRS data object.
dyn	dynamic index.
x_pos	x index.
y_pos	y index.
z_pos	z index.
coil	coil element index.

Value

MRS data vector.

mvfftshift *Perform a fftshift on a matrix, with each column replaced by its shifted result.*

Description

Perform a fftshift on a matrix, with each column replaced by its shifted result.

Usage

mvfftshift(x)

Arguments

x matrix input.

Value

output matrix.

mvifftshift *Perform an ifftshift on a matrix, with each column replaced by its shifted result.*

Description

Perform an ifftshift on a matrix, with each column replaced by its shifted result.

Usage

mvifftshift(x)

Arguments

x matrix input.

Value

output matrix.

n2coord	<i>Print fit coordinates from a single index.</i>
---------	---

Description

Print fit coordinates from a single index.

Usage

```
n2coord(n, fit_res)
```

Arguments

n	fit index.
fit_res	fit_result object.

Ncoils	<i>Return the total number of coil elements in an MRS dataset.</i>
--------	--

Description

Return the total number of coil elements in an MRS dataset.

Usage

```
Ncoils(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

Ndyncs	<i>Return the total number of dynamic scans in an MRS dataset.</i>
--------	--

Description

Return the total number of dynamic scans in an MRS dataset.

Usage

```
Ndyncs(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

nifti_flip_lr	<i>Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).</i>
---------------	--

Description

Flip the x data dimension order of a nifti image. This corresponds to flipping MRI data in the left-right direction, assuming the data is saved in neurological format (can check with fsorient program).

Usage

```
nifti_flip_lr(x)
```

Arguments

x nifti object to be processed.

Value

nifti object with reversed x data direction.

Npts	<i>Return the number of data points in an MRS dataset.</i>
------	--

Description

Return the number of data points in an MRS dataset.

Usage

```
Npts(mrs_data)
```

Arguments

mrs_data MRS data.

Value

number of data points.

Nspec	<i>Return the total number of spectra in an MRS dataset.</i>
-------	--

Description

Return the total number of spectra in an MRS dataset.

Usage

Nspec(mrs_data)

Arguments

mrs_data MRS data.

Nx	<i>Return the total number of x locations in an MRS dataset.</i>
----	--

Description

Return the total number of x locations in an MRS dataset.

Usage

Nx(mrs_data)

Arguments

mrs_data MRS data.

Ny	<i>Return the total number of y locations in an MRS dataset.</i>
----	--

Description

Return the total number of y locations in an MRS dataset.

Usage

Ny(mrs_data)

Arguments

mrs_data MRS data.

Nz	<i>Return the total number of z locations in an MRS dataset.</i>
----	--

Description

Return the total number of z locations in an MRS dataset.

Usage

```
Nz(mrs_data)
```

Arguments

mrs_data	MRS data.
----------	-----------

ortho3	<i>Display an orthographic projection plot of a nifti object.</i>
--------	---

Description

Display an orthographic projection plot of a nifti object.

Usage

```
ortho3(  
  underlay,  
  overlay = NULL,  
  xyz = NULL,  
  zlim = NULL,  
  zlim_ol = NULL,  
  alpha = 0.7,  
  col_ol = viridisLite::viridis(64),  
  orient_lab = TRUE,  
  rescale = 1,  
  crosshairs = TRUE,  
  ch_lwd = 1,  
  colourbar = TRUE,  
  bg = "black",  
  mar = c(0, 0, 0, 0),  
  smallplot = c(0.63, 0.65, 0.07, 0.42)  
)
```

Arguments

underlay	underlay image to be shown in grayscale.
overlay	optional overlay image.
xyz	x, y, z slice coordinates to display.
zlim	underlay intensity limits.
zlim_ol	overlay intensity limits.
alpha	transparency of overlay.
col_ol	colour palette of overlay.
orient_lab	display orientation labels (default TRUE).
rescale	rescale factor for the underlay and overlay images.
crosshairs	display the crosshairs (default TRUE).
ch_lwd	crosshair linewidth.
colourbar	display a colourbar for the overlay (default TRUE).
bg	plot background colour.
mar	plot margins.
smallplot	smallplot option for positioning the colourbar.

ortho3_inter

Display an interactive orthographic projection plot of a nifti object.

Description

Display an interactive orthographic projection plot of a nifti object.

Usage

```
ortho3_inter(  
  underlay,  
  overlay = NULL,  
  xyz = NULL,  
  zlim = NULL,  
  zlim_ol = NULL,  
  alpha = 0.7,  
  ...  
)
```

Arguments

underlay	underlay image to be shown in grayscale.
overlay	optional overlay image.
xyz	x, y, z slice coordinates to display.
zlim	underlay intensity limits.
zlim_ol	overlay intensity limits.
alpha	transparency of overlay.
...	other options to be passed to the ortho3 function.

peak_info	<i>Search for the highest peak in a spectral region and return the frequency, height and FWHM.</i>
-----------	--

Description

Search for the highest peak in a spectral region and return the frequency, height and FWHM.

Usage

```
peak_info(
  mrs_data,
  xlim = c(4, 0.5),
  interp_f = 4,
  scale = "ppm",
  mode = "real"
)
```

Arguments

mrs_data	an object of class mrs_data.
xlim	frequency range (default units of PPM) to search for the highest peak.
interp_f	interpolation factor, defaults to 4x.
scale	the units to use for the frequency scale, can be one of: "ppm", "hz" or "points".
mode	spectral mode, can be : "real", "imag" or "mod".

Value

list of arrays containing the highest peak frequency, height and FWHM in units of PPM and Hz.

pg_extrap_xy

Papoulis-Gerchberg (PG) algorithm method for k-space extrapolation.

Description

PG method as described in: Haupt CI, Schuff N, Weiner MW, Maudsley AA. Removal of lipid artifacts in 1H spectroscopic imaging by data extrapolation. Magn Reson Med. 1996 May;35(5):678-87. Extrapolation is performed to expand k-space coverage by a factor of 2, with the aim to reduce Gibbs ringing.

Usage

```
pg_extrap_xy(  
  mrs_data,  
  img_mask = NULL,  
  kspace_mask = NULL,  
  intensity_thresh = 0.15,  
  iters = 50  
)
```

Arguments

mrs_data	MRS data object.
img_mask	a boolean matrix of voxels with strong signals to be extrapolated. Must be twice the dimensions of the input data.
kspace_mask	a boolean matrix of kspace points that have been sampled. Typically a circle for MRSI, but defaults to the full rectangular area of k-space covered by the input data. Must match the x-y dimensions of the input data.
intensity_thresh	used to define img_mask based on the strength of the signal in each voxel. Defaults to intensities greater than 15% of the maximum. Ignored if img_mask is specified as argument.
iters	number of iterations to perform.

Value

extrapolated mrs_data object.

phase	<i>Apply phasing parameters to MRS data.</i>
-------	--

Description

Apply phasing parameters to MRS data.

Usage

```
phase(mrs_data, zero_order, first_order = 0)
```

Arguments

mrs_data	MRS data.
zero_order	zero'th order phase term in degrees.
first_order	first order (frequency dependent) phase term in ms.

Value

MRS data with applied phase parameters.

plot.fit_result	<i>Plot the fitting results of an object of class fit_result.</i>
-----------------	---

Description

Plot the fitting results of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'
plot(
  x,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  xlim = NULL,
  data_only = FALSE,
  label = NULL,
  plot_sigs = NULL,
  n = NULL,
  sub_b1 = FALSE,
  mar = NULL,
```

```

    restore_def_par = TRUE,
    ylim = NULL,
    y_scale = FALSE,
    show_grid = TRUE,
    grid_nx = NULL,
    grid_ny = NA,
    ...
)

```

Arguments

x	fit_result object.
dyn	the dynamic index to plot.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
data_only	display only the processed data (logical).
label	character string to add to the top left of the plot window.
plot_sigs	a character vector of signal names to add to the plot.
n	single index element to plot (overrides other indices when given).
sub_bl	subtract the baseline from the data and fit (logical).
mar	option to adjust the plot margins. See ?par.
restore_def_par	restore default plotting par values after the plot has been made.
ylim	range of values to display on the y-axis, eg ylim = c(0,10).
y_scale	option to display the y-axis values (logical).
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
...	further arguments to plot method.

`plot.mrs_data`*Plotting method for objects of class mrs_data.*

Description

Plotting method for objects of class `mrs_data`.

Usage

```
## S3 method for class 'mrs_data'
plot(
  x,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  fd = TRUE,
  x_units = NULL,
  xlim = NULL,
  y_scale = FALSE,
  x_ax = TRUE,
  mode = "re",
  lwd = NULL,
  bty = NULL,
  label = "",
  restore_def_par = TRUE,
  mar = NULL,
  xaxis_lab = NULL,
  xat = NULL,
  xlabs = TRUE,
  yat = NULL,
  ylabs = TRUE,
  show_grid = TRUE,
  grid_nx = NULL,
  grid_ny = NA,
  col = NULL,
  alpha = NULL,
  ...
)
```

Arguments

<code>x</code>	object of class <code>mrs_data</code> .
<code>dyn</code>	the dynamic index to plot.
<code>x_pos</code>	the x index to plot.

y_pos	the y index to plot.
z_pos	the z index to plot.
coil	the coil element number to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
xlim	the range of values to display on the x-axis, eg xlim = c(4,1).
y_scale	option to display the y-axis values (logical).
x_ax	option to display the x-axis values (logical).
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
lwd	plot linewidth.
bty	option to draw a box around the plot. See ?par.
label	character string to add to the top left of the plot window.
restore_def_par	restore default plotting par values after the plot has been made.
mar	option to adjust the plot margins. See ?par.
xaxis_lab	x-axis label.
xat	x-axis tick label values.
xlabs	x-axis tick labels.
yat	y-axis tick label values.
ylabs	y-axis tick labels.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
col	set the line colour, eg col = rgb(0.5, 0.5, 0.5).
alpha	set the line transparency, eg alpha = 0.5 is 50% transparency. Overrides any transparency levels set by col.
...	other arguments to pass to the plot method.

plot_bc	<i>Convenience function to plot a baseline estimate with the original data.</i>
---------	---

Description

Convenience function to plot a baseline estimate with the original data.

Usage

```
plot_bc(orig_data, bc_data, ...)
```

Arguments

orig_data	the original data.
bc_data	the baseline corrected data.
...	other arguments to pass to the stackplot function.

plot_slice_fit	<i>Plot a 2D slice from an MRSI fit result object.</i>
----------------	--

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit(
  fit_res,
  map,
  map_denom = NULL,
  slice = 1,
  zlim = NULL,
  interp = 1
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.

plot_slice_fit_inter *Plot a 2D slice from an MRSI fit result object.*

Description

Plot a 2D slice from an MRSI fit result object.

Usage

```
plot_slice_fit_inter(
  fit_res,
  map = NULL,
  map_denom = NULL,
  slice = 1,
  zlim = NULL,
  interp = 1,
  xlim = NULL
)
```

Arguments

fit_res	fit_result object.
map	fit result values to display as a colour map. Can be specified as a character string or array of numeric values. Defaults to "tNAA".
map_denom	fit result values to divide the map argument by. Can be specified as a character string (eg "tCr") or array of numeric values.
slice	slice to plot in the z direction.
zlim	range of values to plot.
interp	interpolation factor.
xlim	spectral plot limits for the x axis.

plot_slice_map *Plot a slice from a 7 dimensional array.*

Description

Plot a slice from a 7 dimensional array.

Usage

```

plot_slice_map(
    data,
    zlim = NULL,
    mask_map = NULL,
    mask_cutoff = 20,
    interp = 1,
    slice = 1,
    dyn = 1,
    coil = 1,
    ref = 1,
    denom = NULL,
    horizontal = FALSE
)

```

Arguments

data	7d array of values to be plotted.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
slice	the slice index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
ref	reference index to plot.
denom	map to use as a denominator.
horizontal	display the colourbar horizontally (logical).

plot_slice_map_inter *Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.*

Description

Plot an interactive slice map from a data array where voxels can be selected to display a corresponding spectrum.

Usage

```
plot_slice_map_inter(  
  mrs_data,  
  map = NULL,  
  xlim = NULL,  
  slice = 1,  
  zlim = NULL,  
  mask_map = NULL,  
  denom = NULL,  
  mask_cutoff = 20,  
  interp = 1,  
  mode = "re",  
  y_scale = FALSE,  
  ylim = NULL,  
  coil = 1,  
  fd = TRUE  
)
```

Arguments

mrs_data	spectral data.
map	array of values to be plotted, defaults to the integration of the modulus of the full spectral width.
xlim	spectral region to plot.
slice	the slice index to plot.
zlim	smallest and largest values to be plotted.
mask_map	matching map with logical values to indicate if the corresponding values should be plotted.
denom	map to use as a denominator.
mask_cutoff	minimum values to plot (as a percentage of the maximum).
interp	map interpolation factor.
mode	representation of the complex spectrum to be plotted, can be one of: "re", "im", "mod" or "arg".
y_scale	option to display the y-axis values (logical).
ylim	intensity range to plot.
coil	coil element to plot.
fd	display data in the frequency-domain (default), or time-domain (logical).

plot_voi_overlay *Plot a volume as an image overlay.*

Description

Plot a volume as an image overlay.

Usage

```
plot_voi_overlay(mri, voi, export_path = NULL, zlim = NULL, ...)
```

Arguments

mri	image data as a nifti object or path to data file.
voi	volume data as a nifti object or path to data file.
export_path	optional path to save the image in png format.
zlim	underlay intensity limits.
...	additional arguments to the ortho3 function.

plot_voi_overlay_seg *Plot a volume as an overlay on a segmented brain volume.*

Description

Plot a volume as an overlay on a segmented brain volume.

Usage

```
plot_voi_overlay_seg(mri_seg, voi, export_path = NULL, ...)
```

Arguments

mri_seg	segmented brain volume as a nifti object.
voi	volume data as a nifti object.
export_path	optional path to save the image in png format.
...	additional arguments to the ortho3 function.

ppm *Return the ppm scale of an MRS dataset or fit result.*

Description

Return the ppm scale of an MRS dataset or fit result.

Usage

```
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)

## S3 method for class 'mrs_data'
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)

## S3 method for class 'fit_result'
ppm(x, ft = NULL, ref = NULL, fs = NULL, N = NULL)
```

Arguments

x	MRS dataset or fit result.
ft	transmitter frequency in Hz, does not apply when the object is a fit result.
ref	reference value for ppm scale, does not apply when the object is a fit result.
fs	sampling frequency in Hz, does not apply when the object is a fit result.
N	number of data points in the spectral dimension, does not apply when the object is a fit result.

Value

ppm scale.

precomp *Save function results to file and load on subsequent calls to avoid repeat computation.*

Description

Save function results to file and load on subsequent calls to avoid repeat computation.

Usage

```
precomp(file, fun, ...)
```

Arguments

file	file name to write the results.
fun	function to run.
...	arguments to be passed to fun.

print.fit_result	<i>Print a summary of an object of class fit_result.</i>
------------------	--

Description

Print a summary of an object of class fit_result.

Usage

```
## S3 method for class 'fit_result'  
print(x, ...)
```

Arguments

x	fit_result object.
...	further arguments.

print.mrs_data	<i>Print a summary of mrs_data parameters.</i>
----------------	--

Description

Print a summary of mrs_data parameters.

Usage

```
## S3 method for class 'mrs_data'  
print(x, full = FALSE, ...)
```

Arguments

x	mrs_data object.
full	print all parameters (default FALSE).
...	further arguments.

qn_states	<i>Get the quantum coherence matrix for a spin system.</i>
-----------	--

Description

Get the quantum coherence matrix for a spin system.

Usage

```
qn_states(sys)
```

Arguments

sys spin system object.

Value

quantum coherence number matrix.

rats	<i>Robust Alignment to a Target Spectrum (RATS).</i>
------	--

Description

Robust Alignment to a Target Spectrum (RATS).

Usage

```
rats(  
  mrs_data,  
  ref = NULL,  
  xlim = c(4, 0.5),  
  max_shift = 20,  
  p_deg = 2,  
  sp_N = 2,  
  sp_deg = 3,  
  max_t = 0.2,  
  basis_type = "poly",  
  rescale_output = TRUE,  
  phase_corr = TRUE,  
  ret_corr_only = FALSE  
)
```

Arguments

mrs_data	MRS data to be corrected.
ref	optional MRS data to use as a reference, the mean of all dynamics is used if this argument is not supplied.
xlim	optional frequency range to perform optimisation, set to NULL to use the full range.
max_shift	maximum allowable frequency shift in Hz.
p_deg	polynomial degree used for baseline modelling. Negative values disable baseline modelling.
sp_N	number of spline functions, note the true number will be sp_N + sp_deg.
sp_deg	degree of spline functions.
max_t	truncate the FID when longer than max_t to reduce time taken, set to NULL to use the entire FID.
basis_type	may be one of "poly" or "spline".
rescale_output	rescale the bl_matched_spec and bl output to improve consistency between dynamic scans.
phase_corr	apply phase correction (in addition to frequency). TRUE by default.
ret_corr_only	return the corrected mrs_data object only.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

Re.mrs_data

Apply Re operator to an MRS dataset.

Description

Apply Re operator to an MRS dataset.

Usage

```
## S3 method for class 'mrs_data'
Re(z)
```

Arguments

z MRS data.

Value

MRS data following Re operator.

read_basis	<i>Read a basis file in LCModel .basis format.</i>
------------	--

Description

Read a basis file in LCModel .basis format.

Usage

```
read_basis(basis_file, ref = def_ref(), sort_basis = TRUE)
```

Arguments

basis_file	path to basis file.
ref	assumed ppm reference value.
sort_basis	sort the basis set based on signal names.

Value

basis object.

read_basis_ac	<i>Read a basis file in LCModel .basis format (for testing only).</i>
---------------	---

Description

Read a basis file in LCModel .basis format (for testing only).

Usage

```
read_basis_ac(basis_file, ref = def_ref(), sort_basis = TRUE)
```

Arguments

basis_file	path to basis file.
ref	assumed ppm reference value.
sort_basis	sort the basis set based on signal names.

Value

basis object.

read_ima_coil_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.</i>
-------------------	--

Description

Read a directory containing Siemens MRS IMA files and combine along the coil dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required between two directories.

Usage

```
read_ima_coil_dir(dir, extra = NULL)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Value

mrs_data object.

read_ima_dyn_dir	<i>Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.</i>
------------------	---

Description

Read a directory containing Siemens MRS IMA files and combine along the dynamic dimension. Note that the coil ID is inferred from the sorted file name and should be checked when consistency is required.

Usage

```
read_ima_dyn_dir(dir, extra = NULL)
```

Arguments

dir	data directory path.
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Value

mrs_data object.

read_lcm_coord	<i>Read an LCModel formatted coord file containing fit information.</i>
----------------	---

Description

Read an LCModel formatted coord file containing fit information.

Usage

```
read_lcm_coord(coord_f)
```

Arguments

coord_f path to the coord file.

Value

list containing a table of fit point and results structure containing signal amplitudes, errors and fitting diagnostics.

read_mrs	<i>Read MRS data from a file.</i>
----------	-----------------------------------

Description

Read MRS data from a file.

Usage

```
read_mrs(
  fname,
  format = NULL,
  ft = NULL,
  fs = NULL,
  ref = NULL,
  n_ref_scans = NULL,
  full_fid = FALSE,
  omit_svs_ref_scans = TRUE,
  verbose = FALSE,
  extra = NULL
)
```

Arguments

fname	filename of the dpt format MRS data.
format	string describing the data format. Must be one of the following : "spar_sdat", "rda", "dicom", "twix", "pfile", "list_data", "paravis", "dpt", "lcm_raw", "rds", "nifti", "varian". If not specified, the format will be guessed from the filename extension.
ft	transmitter frequency in Hz (required for list_data format).
fs	sampling frequency in Hz (required for list_data format).
ref	reference value for ppm scale (required for list_data format).
n_ref_scans	override the number of water reference scans detected in the file header (GE p-file only).
full_fid	export all data points, including those before the start of the FID (default = FALSE), TWIX format only.
omit_svs_ref_scans	remove any reference scans sometimes saved in SVS twix data (default = TRUE).
verbose	print data file information (default = FALSE).
extra	an optional data frame to provide additional variables for use in subsequent analysis steps, eg id or grouping variables.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package = "spant")
mrs_data <- read_mrs(fname)
print(mrs_data)
```

read_mrs_tqn	<i>Read MRS data using the TARQUIN software package.</i>
--------------	--

Description

Read MRS data using the TARQUIN software package.

Usage

```
read_mrs_tqn(fname, fname_ref = NA, format, id = NA, group = NA)
```

Arguments

fname	the filename containing the MRS data.
fname_ref	a second filename containing reference MRS data.
format	format of the MRS data. Can be one of the following: siemens, philips, ge, dcm, dpt, rda, lcm, varian, bruker, jmrui_txt.
id	optional ID string.
group	optional group string.

Value

MRS data object.

Examples

```
fname <- system.file("extdata", "philips_spar_sdat_WS.SDAT", package="spant")
## Not run:
mrs_data <- read_mrs_tqn(fname, format="philips")

## End(Not run)
```

read_siemens_txt_hdr *Read the text format header found in Siemens IMA and TWIX data files.*

Description

Read the text format header found in Siemens IMA and TWIX data files.

Usage

```
read_siemens_txt_hdr(input, version = "vd", verbose)
```

Arguments

input	file name to read or raw data.
version	software version, can be "vb" or "vd".
verbose	print information to the console.

Value

a list of parameter values

read_tqn_fit	<i>Reader for csv fit results generated by TARQUIN.</i>
--------------	---

Description

Reader for csv fit results generated by TARQUIN.

Usage

```
read_tqn_fit(fit_f)
```

Arguments

fit_f TARQUIN fit file.

Value

A data frame of the fit data points.

Examples

```
## Not run:  
fit <- read_tqn_fit(system.file("extdata", "fit.csv", package="spant"))  
  
## End(Not run)
```

read_tqn_result	<i>Reader for csv results generated by TARQUIN.</i>
-----------------	---

Description

Reader for csv results generated by TARQUIN.

Usage

```
read_tqn_result(result_f, remove_rcs = TRUE)
```

Arguments

result_f TARQUIN result file.
remove_rcs omit row, column and slice ids from output.

Value

list of amplitudes, crlbs and diagnostics.

Examples

```
## Not run:
result <- read_tqn_result(system.file("extdata", "result.csv", package="spant"))

## End(Not run)
```

recon_twix_2d_mrsi	<i>Reconstruct 2D MRSI data from a twix file loaded with read_mrs.</i>
--------------------	--

Description

Reconstruct 2D MRSI data from a twix file loaded with read_mrs.

Usage

```
recon_twix_2d_mrsi(twix_mrs)
```

Arguments

twix_mrs	raw dynamic data.
----------	-------------------

Value

reconstructed data.

rectangular_mask	<i>Create a rectangular mask stored as a matrix of logical values.</i>
------------------	--

Description

Create a rectangular mask stored as a matrix of logical values.

Usage

```
rectangular_mask(xN, yN, x0, y0, xw, yw, angle)
```

Arguments

xN	number of pixels in the x dimension.
yN	number of pixels in the y dimension.
x0	centre of rectangle in the x direction in units of pixels.
y0	centre of rectangle in the y direction in units of pixels.
xw	width in the x direction in units of pixels.
yw	width in the y direction in units of pixels.
angle	angle of rotation in degrees.

Value

logical mask matrix with dimensions fov_yN x fov_xN.

rep_array_dim	<i>Repeat an array over a given dimension.</i>
---------------	--

Description

Repeat an array over a given dimension.

Usage

```
rep_array_dim(x, rep_dim, n)
```

Arguments

x	array.
rep_dim	dimension to extend.
n	number of times to repeat.

Value

extended array.

rep_dyn	<i>Replicate a scan in the dynamic dimension.</i>
---------	---

Description

Replicate a scan in the dynamic dimension.

Usage

```
rep_dyn(mrs_data, times)
```

Arguments

mrs_data	MRS data to be replicated.
times	number of times to replicate.

Value

replicated data object.

rep_mrs	<i>Replicate a scan over a given dimension.</i>
---------	---

Description

Replicate a scan over a given dimension.

Usage

```
rep_mrs(  
  mrs_data,  
  x_rep = 1,  
  y_rep = 1,  
  z_rep = 1,  
  dyn_rep = 1,  
  coil_rep = 1,  
  warn = TRUE  
)
```

Arguments

mrs_data	MRS data to be replicated.
x_rep	number of x replications.
y_rep	number of y replications.
z_rep	number of z replications.
dyn_rep	number of dynamic replications.
coil_rep	number of coil replications.
warn	print a warning when the data dimensions do not change.

Value

replicated data object.

resample_img	<i>Resample an image to match a target image space.</i>
--------------	---

Description

Resample an image to match a target image space.

Usage

```
resample_img(source, target, interp = 3L)
```

Arguments

source	image data as a nifti object.
target	image data as a nifti object.
interp	interpolation parameter, see niftyreg.linear definition.

Value

resampled image data as a nifti object.

resample_voi	<i>Resample a VOI to match a target image space using nearest-neighbour interpolation.</i>
--------------	--

Description

Resample a VOI to match a target image space using nearest-neighbour interpolation.

Usage

```
resample_voi(voi, mri)
```

Arguments

voi	volume data as a nifti object.
mri	image data as a nifti object.

Value

volume data as a nifti object.

reslice_to_mrs	<i>Reslice a nifti object to match the orientation of mrs data.</i>
----------------	---

Description

Reslice a nifti object to match the orientation of mrs data.

Usage

```
reslice_to_mrs(mri, mrs)
```

Arguments

mri	nifti object to be resliced.
mrs	mrs_data object for the target orientation.

Value

resliced imaging data.

reson_table2mrs_data *Generate mrs_data from a table of single Lorentzian resonances.*

Description

Generate mrs_data from a table of single Lorentzian resonances.

Usage

```
reson_table2mrs_data(
  reson_table,
  acq_paras = def_acq_paras(),
  back_extrap_pts = 0
)
```

Arguments

reson_table as produced by the hsvd function.
 acq_paras list of acquisition parameters. See
 back_extrap_pts number of data points to back extrapolate [def_acq_paras](#)

Value

mrs_data object.

re_weighting *Apply a weighting to the FID to enhance spectral resolution.*

Description

Apply a weighting to the FID to enhance spectral resolution.

Usage

```
re_weighting(mrs_data, re, alpha)
```

Arguments

mrs_data data to be enhanced.
 re resolution enhancement factor (rising exponential factor).
 alpha alpha factor (Gaussian decay)

Value

resolution enhanced mrs_data.

rm_dyns	<i>Remove a subset of dynamic scans.</i>
---------	--

Description

Remove a subset of dynamic scans.

Usage

```
rm_dyns(mrs_data, subset)
```

Arguments

mrs_data	dynamic MRS data.
subset	vector containing indices to the dynamic scans to be removed.

Value

MRS data without the specified dynamic scans.

scale_amp_molal_pvc	<i>Apply partial volume correction to a fitting result object.</i>
---------------------	--

Description

Apply partial volume correction to a fitting result object.

Usage

```
scale_amp_molal_pvc(fit_result, ref_data, p_vols, te, tr, ...)
```

Arguments

fit_result	result object generated from fitting.
ref_data	water reference MRS data object.
p_vols	a numeric vector of partial volumes.
te	the MRS TE in seconds.
tr	the MRS TR in seconds.
...	additional arguments to get_td_amp function.

Value

A fit_result object with a rescaled results table.

scale_amp_molar	<i>Apply water reference scaling to a fitting results object to yield metabolite quantities in millimolar (mM) units (mol/litre).</i>
-----------------	---

Description

See the LCMoel manual section on water-scaling for details on the assumptions and relevant references.

Usage

```
scale_amp_molar(fit_result, ref_data, w_att = 0.7, w_conc = 35880, ...)
```

Arguments

fit_result	a result object generated from fitting.
ref_data	water reference MRS data object.
w_att	water attenuation factor (default = 0.7).
w_conc	assumed water concentration (default = 35880). Default value corresponds to typical white matter. Set to 43300 for gray matter, and 55556 for phantom measurements.
...	additional arguments to get_td_amp function.

Value

a fit_result object with a rescaled results table.

scale_amp_ratio	<i>Scale fitted amplitudes to a ratio of signal amplitude.</i>
-----------------	--

Description

Scale fitted amplitudes to a ratio of signal amplitude.

Usage

```
scale_amp_ratio(fit_result, name)
```

Arguments

fit_result	a result object generated from fitting.
name	the signal name to use as a denominator (usually, "tCr" or "tNAA").

Value

a fit_result object with a rescaled results table.

scale_amp_water_ratio *Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.*

Description

Scale metabolite amplitudes as a ratio to the unsuppressed water amplitude.

Usage

```
scale_amp_water_ratio(fit_result, ref_data, ...)
```

Arguments

fit_result a result object generated from fitting.
ref_data a water reference MRS data object.
... additional arguments to get_td_amp function.

Value

a fit_result object with a rescaled results table.

scale_mrs_amp *Scale an mrs_data object by a scalar or vector or amplitudes.*

Description

Scale an mrs_data object by a scalar or vector or amplitudes.

Usage

```
scale_mrs_amp(mrs_data, amp)
```

Arguments

mrs_data data to be scaled.
amp multiplicative factor, must have length equal to 1 or Nspec(mrs_data).

Value

mrs_data object multiplied by the amplitude scale factor.

scale_spec	<i>Scale mrs_data to a spectral region.</i>
------------	---

Description

Scale mrs_data to a spectral region.

Usage

```
scale_spec(
  mrs_data,
  xlim = NULL,
  operator = "sum",
  freq_scale = "ppm",
  mode = "re",
  mean_dyns = TRUE
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "l2", "max", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "Hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".
mean_dyns	mean the dynamic scans before applying the operator. The same scaling value will be applied to each individual dynamic.

Value

normalised data.

sd	<i>Calculate the standard deviation spectrum from an mrs_data object.</i>
----	---

Description

Calculate the standard deviation spectrum from an mrs_data object.

Usage

```
sd(x, na.rm)
```

Arguments

x object of class `mrs_data`.
 na.rm remove NA values.

Value

sd `mrs_data` object.

sd.mrs_data *Calculate the standard deviation spectrum from an mrs_data object.*

Description

Calculate the standard deviation spectrum from an `mrs_data` object.

Usage

```
## S3 method for class 'mrs_data'
sd(x, na.rm = FALSE)
```

Arguments

x object of class `mrs_data`.
 na.rm remove NA values.

Value

sd `mrs_data` object.

seconds *Return a time scale vector to match the FID of an MRS data object.*

Description

Return a time scale vector to match the FID of an MRS data object.

Usage

```
seconds(mrs_data)
```

Arguments

mrs_data MRS data.

Value

time scale vector in units of seconds.

seq_cpmg_ideal	<i>CPMG style sequence with ideal pulses.</i>
----------------	---

Description

CPMG style sequence with ideal pulses.

Usage

```
seq_cpmg_ideal(spin_params, ft, ref, TE = 0.03, echoes = 4)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	echo time in seconds.
echoes	number of echoes.

Value

list of resonance amplitudes and frequencies.

seq_mega_press_ideal	<i>MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.</i>
----------------------	--

Description

MEGA-PRESS sequence with ideal localisation pulses and Gaussian shaped editing pulse.

Usage

```
seq_mega_press_ideal(  
  spin_params,  
  ft,  
  ref,  
  ed_freq = 1.89,  
  TE1 = 0.015,  
  TE2 = 0.053,  
  BW = 110,  
  steps = 50  
)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
ed_freq	editing pulse frequency in ppm.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.
BW	editing pulse bandwidth in Hz.
steps	number of hard pulses used to approximate the editing pulse.

Value

list of resonance amplitudes and frequencies.

seq_press_ideal	<i>PRESS sequence with ideal pulses.</i>
-----------------	--

Description

PRESS sequence with ideal pulses.

Usage

```
seq_press_ideal(spin_params, ft, ref, TE1 = 0.01, TE2 = 0.02)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	TE1 sequence parameter in seconds (TE=TE1+TE2).
TE2	TE2 sequence parameter in seconds.

Value

list of resonance amplitudes and frequencies.

seq_pulse_acquire *Simple pulse and acquire sequence with ideal pulses.*

Description

Simple pulse and acquire sequence with ideal pulses.

Usage

```
seq_pulse_acquire(spin_params, ft, ref)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.

Value

list of resonance amplitudes and frequencies.

seq_pulse_acquire_31p *Simple pulse and acquire sequence with ideal pulses.*

Description

Simple pulse and acquire sequence with ideal pulses.

Usage

```
seq_pulse_acquire_31p(spin_params, ft, ref)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.

Value

list of resonance amplitudes and frequencies.

seq_slaser_ideal *sLASER sequence with ideal pulses.*

Description

sLASER sequence with ideal pulses.

Usage

```
seq_slaser_ideal(spin_params, ft, ref, TE1 = 0.008, TE2 = 0.011, TE3 = 0.009)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE1	first echo time (between exc. and 1st echo) in seconds.
TE2	second echo time (between 2nd echo and 4th echo) in seconds.
TE3	third echo time (between 4th echo and 5th echo) in seconds.

Value

list of resonance amplitudes and frequencies.

seq_spin_echo_ideal *Spin echo sequence with ideal pulses.*

Description

Spin echo sequence with ideal pulses.

Usage

```
seq_spin_echo_ideal(spin_params, ft, ref, TE = 0.03)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	echo time in seconds.

Value

list of resonance amplitudes and frequencies.

seq_spin_echo_ideal_31p

Spin echo sequence with ideal pulses.

Description

Spin echo sequence with ideal pulses.

Usage

```
seq_spin_echo_ideal_31p(spin_params, ft, ref, TE = 0.03)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	echo time in seconds.

Value

list of resonance amplitudes and frequencies.

seq_steam_ideal

STEAM sequence with ideal pulses.

Description

STEAM sequence with ideal pulses.

Usage

```
seq_steam_ideal(spin_params, ft, ref, TE = 0.03, TM = 0.02)
```

Arguments

spin_params	spin system definition.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
TE	sequence parameter in seconds.
TM	sequence parameter in seconds.

Value

list of resonance amplitudes and frequencies.

set_def_acq_paras *Set the default acquisition parameters.*

Description

Set the default acquisition parameters.

Usage

```
set_def_acq_paras(  
  ft = getOption("spant.def_ft"),  
  fs = getOption("spant.def_fs"),  
  N = getOption("spant.def_N"),  
  ref = getOption("spant.def_ref"),  
  nuc = getOption("spant.nuc")  
)
```

Arguments

ft	transmitter frequency in Hz.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
nuc	resonant nucleus.

set_lcm_cmd *Set the command to run the LCModel command-line program.*

Description

Set the command to run the LCModel command-line program.

Usage

```
set_lcm_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

set_lw	<i>Apply line-broadening to an mrs_data object to achieve a specified linewidth.</i>
--------	--

Description

Apply line-broadening to an mrs_data object to achieve a specified linewidth.

Usage

```
set_lw(mrs_data, lw, xlim = c(4, 0.5))
```

Arguments

mrs_data	data in.
lw	target linewidth in units of ppm.
xlim	region to search for peaks to obtain a linewidth estimate.

Value

line-broadened data.

set_mask_xy_mat	<i>Set the masked voxels in a 2D MRSI dataset to given spectrum.</i>
-----------------	--

Description

Set the masked voxels in a 2D MRSI dataset to given spectrum.

Usage

```
set_mask_xy_mat(mrs_data, mask, mask_mrs_data)
```

Arguments

mrs_data	MRSI data object.
mask	matrix of boolean values specifying the voxels to set, where a value of TRUE indicates the voxel should be set to mask_mrs_data.
mask_mrs_data	the spectral data to be assigned to the masked voxels.

Value

updated dataset.

set_precomp_mode	<i>Set the precompute mode.</i>
------------------	---------------------------------

Description

Set the precompute mode.

Usage

```
set_precomp_mode(mode = NA)
```

Arguments

mode	can be one of: "default", "overwrite", "clean" or "disabled".
------	---

set_precomp_verbose	<i>Set the verbosity of the precompute function.</i>
---------------------	--

Description

Set the verbosity of the precompute function.

Usage

```
set_precomp_verbose(verbose = NA)
```

Arguments

verbose	can be TRUE or FALSE.
---------	-----------------------

set_ref	<i>Set the ppm reference value (eg ppm value at 0Hz).</i>
---------	---

Description

Set the ppm reference value (eg ppm value at 0Hz).

Usage

```
set_ref(mrs_data, ref)
```

Arguments

mrs_data	MRS data.
ref	reference value for ppm scale.

set_td_pts	<i>Set the number of time-domain data points, truncating or zero-filling as appropriate.</i>
------------	--

Description

Set the number of time-domain data points, truncating or zero-filling as appropriate.

Usage

```
set_td_pts(mrs_data, pts)
```

Arguments

mrs_data	MRS data.
pts	number of data points.

Value

MRS data with pts data points.

set_tqn_cmd	<i>Set the command to run the TARQUIN command-line program.</i>
-------------	---

Description

Set the command to run the TARQUIN command-line program.

Usage

```
set_tqn_cmd(cmd)
```

Arguments

cmd	path to binary.
-----	-----------------

shift	<i>Apply a frequency shift to MRS data.</i>
-------	---

Description

Apply a frequency shift to MRS data.

Usage

```
shift(mrs_data, shift, units = "ppm")
```

Arguments

mrs_data	MRS data.
shift	frequency shift (in ppm by default).
units	of the shift ("ppm" or "hz").

Value

frequency shifted MRS data.

shift_basis	<i>Apply frequency shifts to basis set signals.</i>
-------------	---

Description

Apply frequency shifts to basis set signals.

Usage

```
shift_basis(basis, shifts)
```

Arguments

basis	the basis to apply the shift to.
shifts	a vector of frequency shifts to apply in ppm units. Must be the same length as there are basis elements.

Value

modified basis set object.

sim_basis	<i>Simulate a basis set object.</i>
-----------	-------------------------------------

Description

Simulate a basis set object.

Usage

```
sim_basis(
  mol_list,
  pul_seq = seq_pulse_acquire,
  acq_paras = def_acq_paras(),
  xlim = NULL,
  ...
)
```

Arguments

mol_list	list of mol_parameter objects.
pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	ppm range limiting signals to be simulated.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain	<i>Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.</i>
--------------------	--

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain(
  pul_seq = seq_press_ideal,
  acq_paras = def_acq_paras(),
  xlim = c(0.5, 4.2),
  lcm_compat = FALSE,
  ...
)
```

Arguments

pul_seq	pulse sequence function to use.
acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras .
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
...	extra parameters to pass to the pulse sequence function.

Value

basis object.

sim_basis_1h_brain_press

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Description

Simulate a basis-set suitable for 1H brain MRS analysis acquired with a PRESS sequence. Note, ideal pulses are assumed.

Usage

```
sim_basis_1h_brain_press(
  acq_paras = def_acq_paras(),
  xlim = c(0.5, 4.2),
  lcm_compat = FALSE,
  TE1 = 0.01,
  TE2 = 0.02
)
```

Arguments

acq_paras	list of acquisition parameters or an mrs_data object. See def_acq_paras
xlim	range of frequencies to simulate in ppm.
lcm_compat	exclude lipid and MM signals for use with default LCModel options.
TE1	TE1 of PRESS sequence (TE = TE1 + TE2).
TE2	TE2 of PRESS sequence.

Value

basis object.

sim_basis_tqn	<i>Simulate a basis file using TARQUIN.</i>
---------------	---

Description

Simulate a basis file using TARQUIN.

Usage

```
sim_basis_tqn(  
  fs = def_fs(),  
  ft = def_ft(),  
  N = def_N(),  
  ref = def_ref(),  
  opts = NULL  
)
```

Arguments

fs	sampling frequency
ft	transmitter frequency
N	number of data points
ref	chemical shift reference
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:  
write_basis_tqn('test.basis',mrs_data,c("--echo","0.04"))  
  
## End(Not run)
```

sim_brain_1h	<i>Simulate MRS data with a similar appearance to normal brain (by default).</i>
--------------	--

Description

Simulate MRS data with a similar appearance to normal brain (by default).

Usage

```
sim_brain_1h(
  acq_paras = def_acq_paras(),
  type = "normal_v1",
  pul_seq = seq_press_ideal,
  xlim = c(0.5, 4.2),
  full_output = FALSE,
  amps = NULL,
  ...
)
```

Arguments

acq_paras	list of acquisition parameters or an <code>mrs_data</code> object. See def_acq_paras .
type	type of spectrum, only "normal" is implemented currently.
pul_seq	pulse sequence function to use.
xlim	range of frequencies to simulate in ppm.
full_output	when FALSE (default) only output the simulated MRS data. When TRUE output a list containing the MRS data, basis set object and corresponding amplitudes.
amps	a vector of basis amplitudes may be specified to modify the output spectrum.
...	extra parameters to pass to the pulse sequence function.

Value

see `full_output` option.

sim_mol	<i>Simulate a mol_parameter object.</i>
---------	---

Description

Simulate a `mol_parameter` object.

Usage

```
sim_mol(
  mol,
  pul_seq = seq_pulse_acquire,
  ft = def_ft(),
  ref = def_ref(),
  fs = def_fs(),
  N = def_N(),
  xlim = NULL,
  ...
)
```

Arguments

mol	mol_parameter object.
pul_seq	pulse sequence function to use.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
fs	sampling frequency in Hz.
N	number of data points in the spectral dimension.
xlim	ppm range limiting signals to be simulated.
...	extra parameters to pass to the pulse sequence function.

Value

mrs_data object.

sim_noise	<i>Simulate an mrs_data object containing simulated Gaussian noise.</i>
-----------	---

Description

Simulate an mrs_data object containing simulated Gaussian noise.

Usage

```
sim_noise(
  sd = 0.1,
  fs = def_fs(),
  ft = def_ft(),
  N = def_N(),
  ref = def_ref(),
  dyns = 1,
  fd = TRUE
)
```

Arguments

sd	standard deviation of the noise.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
dyns	number of dynamic scans to generate.
fd	return data in the frequency-domain (TRUE) or time-domain (FALSE)

Value

mrs_data object.

sim_resonances	<i>Simulate a MRS data object containing a set of simulated resonances.</i>
----------------	---

Description

Simulate a MRS data object containing a set of simulated resonances.

Usage

```
sim_resonances(  
  freq = 0,  
  amp = 1,  
  lw = 0,  
  lg = 0,  
  phase = 0,  
  freq_ppm = TRUE,  
  acq_paras = def_acq_paras(),  
  fp_scale = TRUE,  
  back_extrap_pts = 0,  
  sum_resonances = TRUE  
)
```

Arguments

freq	resonance frequency.
amp	resonance amplitude.
lw	line width in Hz.
lg	Lorentz-Gauss lineshape parameter (between 0 and 1).
phase	phase in degrees.
freq_ppm	frequencies are given in ppm units if set to TRUE, otherwise Hz are assumed.
acq_paras	list of acquisition parameters. See def_acq_paras
fp_scale	multiply the first data point by 0.5.
back_extrap_pts	number of data points to back extrapolate.
sum_resonances	sum all resonances (default is TRUE), otherwise return a dynamic mrs_data object.

Value

MRS data object.

Examples

```
sim_data <- sim_resonances(freq = 2, lw = 5)
```

sim_zero	<i>Simulate an mrs_data object containing complex zero valued samples.</i>
----------	--

Description

Simulate an mrs_data object containing complex zero valued samples.

Usage

```
sim_zero(fs = def_fs(), ft = def_ft(), N = def_N(), ref = def_ref(), dyns = 1)
```

Arguments

fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
N	number of data points in the spectral dimension.
ref	reference value for ppm scale.
dyns	number of dynamic scans to generate.

Value

mrs_data object.

sort_basis	<i>Sort the basis-set elements alphabetically.</i>
------------	--

Description

Sort the basis-set elements alphabetically.

Usage

```
sort_basis(basis)
```

Arguments

basis	input basis.
-------	--------------

Value

sorted basis.

spant_abfit_benchmark *Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.*

Description

Simulate and fit some spectra with ABfit for benchmarking purposes. Basic timing and performance metrics will be printed.

Usage

```
spant_abfit_benchmark(noise_reps = 10, return_res = FALSE, opts = abfit_opts())
```

Arguments

noise_reps	number of spectra to fit with differing noise samples.
return_res	return a list of fit_result objects.
opts	ABfit options structure.

spant_mpress_drift *Example MEGA-PRESS data with significant B0 drift.*

Description

Example MEGA-PRESS data with significant B0 drift.

Usage

```
spant_mpress_drift
```

Format

An object of class mrs_data of length 13.

 spant_simulation_benchmark

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Description

Simulate a typical metabolite basis set for benchmarking. Timing metrics will be printed on completion.

Usage

```
spant_simulation_benchmark(sim_reps = 10, N = 1024)
```

Arguments

sim_reps	number of times to simulate the basis set.
N	number of FID data points to simulate.

 spec_op

Perform a mathematical operation on a spectral region.

Description

Perform a mathematical operation on a spectral region.

Usage

```
spec_op(
  mrs_data,
  xlim = NULL,
  operator = "sum",
  freq_scale = "ppm",
  mode = "re"
)
```

Arguments

mrs_data	MRS data.
xlim	spectral range to be integrated (defaults to full range).
operator	can be "sum" (default), "mean", "I2", "max", "min" or "max-min".
freq_scale	units of xlim, can be : "ppm", "hz" or "points".
mode	spectral mode, can be : "re", "im", "mod" or "cplx".

Value

an array of integral values.

spin_sys	<i>Create a spin system object for pulse sequence simulation.</i>
----------	---

Description

Create a spin system object for pulse sequence simulation.

Usage

```
spin_sys(spin_params, ft, ref)
```

Arguments

spin_params	an object describing the spin system properties.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.

Value

spin system object.

spm_pve2categorical	<i>Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.</i>
---------------------	---

Description

Convert SPM style segmentation files to a single categorical image where the numerical values map as: 0) Other, 1) CSF, 2) GM and 3) WM.

Usage

```
spm_pve2categorical(fname)
```

Arguments

fname	any of the segmentation files (eg c1_MY_T1.nii).
-------	--

Value

nifti object.

`ssp`*Signal space projection method for lipid suppression.*

Description

Signal space projection method as described in: Tsai SY, Lin YR, Lin HY, Lin FH. Reduction of lipid contamination in MR spectroscopy imaging using signal space projection. *Magn Reson Med* 2019 Mar;81(3):1486-1498.

Usage

```
ssp(mrs_data, comps = 5, xlim = c(1.5, 0.8))
```

Arguments

<code>mrs_data</code>	MRS data object.
<code>comps</code>	the number of spatial components to use.
<code>xlim</code>	spectral range (in ppm) covering the lipid signals.

Value

lipid suppressed `mrs_data` object.

`stackplot`*Produce a plot with multiple traces.*

Description

Produce a plot with multiple traces.

Usage

```
stackplot(x, ...)
```

Arguments

<code>x</code>	object for plotting.
<code>...</code>	arguments to be passed to methods.

`stackplot.fit_result` *Plot the fitting results of an object of class `fit_result` with individual basis set components shown.*

Description

Plot the fitting results of an object of class `fit_result` with individual basis set components shown.

Usage

```
## S3 method for class 'fit_result'
stackplot(
  x,
  xlim = NULL,
  y_offset = 0,
  dyn = 1,
  x_pos = 1,
  y_pos = 1,
  z_pos = 1,
  coil = 1,
  n = NULL,
  sub_bl = FALSE,
  labels = FALSE,
  label_names = NULL,
  sig_col = "black",
  restore_def_par = TRUE,
  omit_signals = NULL,
  combine_lipmm = FALSE,
  combine_metab = FALSE,
  mar = NULL,
  show_grid = TRUE,
  grid_nx = NULL,
  grid_ny = NA,
  ...
)
```

Arguments

<code>x</code>	<code>fit_result</code> object.
<code>xlim</code>	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
<code>y_offset</code>	separate basis signals in the y-axis direction by this value.
<code>dyn</code>	the dynamic index to plot.
<code>x_pos</code>	the x index to plot.
<code>y_pos</code>	the y index to plot.
<code>z_pos</code>	the z index to plot.

coil	the coil element number to plot.
n	single index element to plot (overrides other indices when given).
sub_bl	subtract the baseline from the data and fit (logical).
labels	print signal labels at the right side of the plot.
label_names	provide a character vector of signal names to replace the defaults determined from the basis set.
sig_col	colour of individual signal components.
restore_def_par	restore default plotting par values after the plot has been made.
omit_signals	a character vector of basis signal names to be removed from the plot.
combine_lipmm	combine all basis signals with names starting with "Lip" or "MM".
combine_metab	combine all basis signals with names not starting with "Lip" or "MM".
mar	option to adjust the plot margins. See ?par.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
...	further arguments to plot method.

stackplot.mrs_data *Stackplot plotting method for objects of class mrs_data.*

Description

Stackplot plotting method for objects of class mrs_data.

Usage

```
## S3 method for class 'mrs_data'
stackplot(
  x,
  xlim = NULL,
  mode = "re",
  x_units = NULL,
  fd = TRUE,
  col = NULL,
  alpha = NULL,
  x_offset = 0,
  y_offset = 0,
  plot_dim = NULL,
  x_pos = NULL,
  y_pos = NULL,
```

```

z_pos = NULL,
dyn = 1,
coil = 1,
bty = NULL,
labels = NULL,
lab_cex = 1,
right_marg = NULL,
bl_lty = NULL,
restore_def_par = TRUE,
show_grid = NULL,
grid_nx = NULL,
grid_ny = NA,
lwd = NULL,
...
)

```

Arguments

x	object of class <code>mrs_data</code> .
xlim	the range of values to display on the x-axis, eg <code>xlim = c(4,1)</code> .
mode	representation of the complex numbers to be plotted, can be one of: "re", "im", "mod" or "arg".
x_units	the units to use for the x-axis, can be one of: "ppm", "hz", "points" or "seconds".
fd	display data in the frequency-domain (default), or time-domain (logical).
col	set the colour of the line, eg <code>col = rgb(1, 0, 0, 0.5)</code> .
alpha	set the line transparency, eg <code>alpha = 0.5</code> is 50% transparency. Overrides any transparency levels set by <code>col</code> .
x_offset	separate plots in the x-axis direction by this value. Default value is 0.
y_offset	separate plots in the y-axis direction by this value.
plot_dim	the dimension to display on the y-axis, can be one of: "dyn", "x", "y", "z", "coil" or NULL. If NULL (the default) all spectra will be collapsed into the dynamic dimension and displayed.
x_pos	the x index to plot.
y_pos	the y index to plot.
z_pos	the z index to plot.
dyn	the dynamic index to plot.
coil	the coil element number to plot.
bty	option to draw a box around the plot. See <code>?par</code> .
labels	add labels to each data item.
lab_cex	label size.
right_marg	change the size of the right plot margin.
bl_lty	linetype for the <code>y = 0</code> baseline trace. A default value NULL results in no baseline being plotted.

restore_def_par	restore default plotting par values after the plot has been made.
show_grid	plot gridlines behind the data (logical). Defaults to TRUE.
grid_nx	number of cells of the grid in x and y direction. When NULL the grid aligns with the tick marks on the corresponding default axis (i.e., tickmarks as computed by axTicks). When NA, no grid lines are drawn in the corresponding direction.
grid_ny	as above.
lwd	plot linewidth.
...	other arguments to pass to the matplot method.

sub_mean_dyns	<i>Subtract the mean dynamic spectrum from a dynamic series.</i>
---------------	--

Description

Subtract the mean dynamic spectrum from a dynamic series.

Usage

```
sub_mean_dyns(mrs_data)
```

Arguments

mrs_data dynamic MRS data.

Value

subtracted data.

sum_coils	<i>Calculate the sum across receiver coil elements.</i>
-----------	---

Description

Calculate the sum across receiver coil elements.

Usage

```
sum_coils(mrs_data)
```

Arguments

mrs_data MRS data split across receiver coil elements.

Value

sum across coil elements.

sum_dyns	<i>Calculate the sum of data dynamics.</i>
----------	--

Description

Calculate the sum of data dynamics.

Usage

```
sum_dyns(mrs_data)
```

Arguments

mrs_data	dynamic MRS data.
----------	-------------------

Value

sum of data dynamics.

sum_mrs	<i>Sum two mrs_data objects.</i>
---------	----------------------------------

Description

Sum two mrs_data objects.

Usage

```
sum_mrs(a, b, force = FALSE)
```

Arguments

a	first mrs_data object to be summed.
b	second mrs_data object to be summed.
force	set to TRUE to force mrs_data objects to be summed, even if they are in different time/frequency domains.

Value

a + b

sum_mrs_list	<i>Return the sum of a list of mrs_data objects.</i>
--------------	--

Description

Return the sum of a list of mrs_data objects.

Usage

```
sum_mrs_list(mrs_list)
```

Arguments

mrs_list list of mrs_data objects.

Value

sum mrs_data object.

svs_1h_brain_analysis	<i>Standard SVS 1H brain analysis pipeline.</i>
-----------------------	---

Description

Standard SVS 1H brain analysis pipeline.

Usage

```
svs_1h_brain_analysis(  
  metab,  
  basis = NULL,  
  w_ref = NULL,  
  mri_seg = NULL,  
  mri = NULL,  
  output_dir = NULL,  
  extra = NULL,  
  decimate = NULL,  
  rats_corr = TRUE,  
  ecc = FALSE,  
  comb_dyns = TRUE,  
  hsvd_filt = FALSE,  
  scale_amps = TRUE,  
  te = NULL,  
  tr = NULL,  
  preproc_only = FALSE,  
  method = "ABFIT",  
  opts = NULL  
)
```

Arguments

metab	filepath or mrs_data object containing MRS metabolite data.
basis	basis set object to use for analysis.
w_ref	filepath or mrs_data object containing MRS water reference data.
mri_seg	filepath or nifti object containing segmented MRI data.
mri	filepath or nifti object containing anatomical MRI data.
output_dir	directory path to output fitting results.
extra	data.frame with one row containing additional information to be attached to the fit results table.
decimate	option to decimate the input data by a factor of two. The default value of NULL does not perform decimation unless the spectral width is greater than 20 PPM.
rats_corr	option to perform rats correction, defaults to TRUE.
ecc	option to perform water reference based eddy current correction, defaults to FALSE.
comb_dyns	option to combine dynamic scans, defaults to TRUE.
hsvd_filt	option to apply hsvd water removal, defaults to FALSE.
scale_amps	option to scale metabolite amplitude estimates, defaults to TRUE.
te	metabolite mrs data echo time in seconds.
tr	metabolite mrs data repetition time in seconds.
preproc_only	only perform the preprocessing steps and omit fitting. The preprocessed metabolite data will be returned in this case.
method	analysis method to use, see fit_mrs help.
opts	options to pass to the analysis method.

Value

a fit_result or mrs_data object depending on the preproc_only option.

svs_1h_brain_batch_analysis

Batch interface to the standard SVS 1H brain analysis pipeline.

Description

Batch interface to the standard SVS 1H brain analysis pipeline.

Usage

```
svs_1h_brain_batch_analysis(
  metab_list,
  w_ref_list = NULL,
  mri_seg_list = NULL,
  mri_list = NULL,
  output_dir_list = NULL,
  extra = NULL,
  ...
)
```

Arguments

metab_list	list of file paths or mrs_data objects containing MRS metabolite data.
w_ref_list	list of file paths or mrs_data objects containing MRS water reference data.
mri_seg_list	list of file paths or nifti objects containing segmented MRI data.
mri_list	list of file paths or nifti objects containing anatomical MRI data.
output_dir_list	list of directory paths to output fitting results.
extra	a data frame with the same number of rows as metab_list, containing additional information to be attached to the fit results table.
...	additional options to be passed to the svs_1h_brain_analysis function.

Value

a list of fit_result objects.

td2fd	<i>Transform time-domain data to the frequency-domain.</i>
-------	--

Description

Transform time-domain data to the frequency-domain.

Usage

```
td2fd(mrs_data)
```

Arguments

mrs_data	MRS data in time-domain representation.
----------	---

Value

MRS data in frequency-domain representation.

tdsr	<i>Time-domain spectral registration.</i>
------	---

Description

An implementation of the method published by Near et al MRM 73:44-50 (2015).

Usage

```
tdsr(mrs_data, ref = NULL, xlim = c(4, 0.5), max_t = 0.2)
```

Arguments

mrs_data	MRS data to be corrected.
ref	optional MRS data to use as a reference, the mean of all dynamics is used if this argument is not supplied.
xlim	optional frequency range to perform optimisation, set to NULL to use the full range.
max_t	truncate the FID when longer than max_t to reduce time taken.

Value

a list containing the corrected data; phase and shift values in units of degrees and Hz respectively.

td_conv_filt	<i>Time-domain convolution based filter.</i>
--------------	--

Description

Time-domain convolution based filter described by: Marion D, Ikura M, Bax A. Improved solvent suppression in one-dimensional and twodimensional NMR spectra by convolution of time-domain data. J Magn Reson 1989;84:425-430.

Usage

```
td_conv_filt(mrs_data, K = 25, ext = 1)
```

Arguments

mrs_data	MRS data to be filtered.
K	window width in data points.
ext	point separation for linear extrapolation.

varpro_3_para_opts	<p><i>Return a list of options for VARPRO based fitting with 3 free parameters:</i></p> <ul style="list-style-type: none"> • <i>zero'th order phase correction</i> • <i>global damping</i> • <i>global frequency shift.</i>
--------------------	--

Description

Return a list of options for VARPRO based fitting with 3 free parameters:

- zero'th order phase correction
- global damping
- global frequency shift.

Usage

```
varpro_3_para_opts(
  nstart = 20,
  init_damping = 2,
  maxiters = 200,
  max_shift = 5,
  max_damping = 5,
  anal_jac = FALSE,
  bl_smth_pts = 80
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum global shift allowed, measured in Hz.
max_damping	maximum damping allowed, FWHM measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

varpro_basic_opts	<i>Return a list of options for a basic VARPRO analysis.</i>
-------------------	--

Description

Return a list of options for a basic VARPRO analysis.

Usage

```
varpro_basic_opts(method = "fd_re", nnls = TRUE)
```

Arguments

method	one of "td", "fd", "fd_re".
nnls	restrict basis amplitudes to non-negative values.

Value

full list of options.

varpro_opts	<i>Return a list of options for VARPRO based fitting.</i>
-------------	---

Description

Return a list of options for VARPRO based fitting.

Usage

```
varpro_opts(  
  nstart = 20,  
  init_g_damping = 2,  
  maxiters = 200,  
  max_shift = 5,  
  max_g_damping = 5,  
  max_ind_damping = 5,  
  anal_jac = TRUE,  
  bl_smth_pts = 80  
)
```

Arguments

nstart	position in the time-domain to start fitting, units of data points.
init_g_damping	starting value for the global Gaussian line-broadening term - measured in Hz.
maxiters	maximum number of levmar iterations to perform.
max_shift	maximum shift allowed to each element in the basis set, measured in Hz.
max_g_damping	maximum permitted global Gaussian line-broadening.
max_ind_damping	maximum permitted Lorentzian line-broadening for each element in the basis set, measured in Hz.
anal_jac	option to use the analytic or numerical Jacobian (logical).
bl_smth_pts	number of data points to use in the baseline smoothing calculation.

Value

list of options.

Examples

```
varpro_opts(nstart = 10)
```

vec2mrs_data	<i>Convert a vector into a mrs_data object.</i>
--------------	---

Description

Convert a vector into a mrs_data object.

Usage

```
vec2mrs_data(  
  vec,  
  fs = def_fs(),  
  ft = def_ft(),  
  ref = def_ref(),  
  nuc = def_nuc(),  
  dyns = 1,  
  fd = FALSE  
)
```

Arguments

vec	the data vector.
fs	sampling frequency in Hz.
ft	transmitter frequency in Hz.
ref	reference value for ppm scale.
nuc	resonant nucleus.
dyns	replicate the data across the dynamic dimension.
fd	flag to indicate if the matrix is in the frequency domain (logical).

Value

mrs_data object.

write_basis	<i>Write a basis object to an LCMModel .basis formatted file.</i>
-------------	---

Description

Write a basis object to an LCMModel .basis formatted file.

Usage

```
write_basis(basis, basis_file, fwhmba = 0.1)
```

Arguments

basis	basis object to be exported.
basis_file	path to basis file to be generated.
fwhmba	parameter used by LCMModel.

write_basis_tqn	<i>Generate a basis file using TARQUIN.</i>
-----------------	---

Description

Generate a basis file using TARQUIN.

Usage

```
write_basis_tqn(basis_file, metab_data, opts = NULL)
```


Arguments

basis_file	filename of the basis file to be generated.
metab_data	MRS data object to match the generated basis parameters.
opts	list of options to pass to TARQUIN.

Examples

```
## Not run:
write_basis_tqn('test.basis',mrs_data,c("--echo","0.04"))

## End(Not run)
```

write_mrs	<i>Write MRS data object to file.</i>
-----------	---------------------------------------

Description

Write MRS data object to file.

Usage

```
write_mrs(mrs_data, fname, format = NULL)
```

Arguments

mrs_data	object to be written to file.
fname	the filename of the output.
format	string describing the data format. Must be one of the following : "nifti", "dpt", "lcm_raw", "rds". If not specified, the format will be guessed from the filename extension.

write_mrs_nifti	<i>Write MRS data object to file in NIFTI format.</i>
-----------------	---

Description

Write MRS data object to file in NIFTI format.

Usage

```
write_mrs_nifti(mrs_data, fname)
```

Arguments

mrs_data	object to be written to file.
fname	the filename of the output NIFTI MRS data.

zero_fade_spec	<i>Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.</i>
----------------	---

Description

Fade a spectrum to zero by frequency domain multiplication with a tanh function. Note this operation distorts data points at the end of the FID.

Usage

```
zero_fade_spec(mrs_data, start_ppm, end_ppm)
```

Arguments

mrs_data	data to be faded.
start_ppm	start point of the fade in ppm units.
end_ppm	end point of the fade in ppm units.

Value

modified mrs_data object.

zero_nzoc	<i>Zero all non-zero-order coherences.</i>
-----------	--

Description

Zero all non-zero-order coherences.

Usage

```
zero_nzoc(sys, rho)
```

Arguments

sys	spin system object.
rho	density matrix.

Value

density matrix.

zf *Zero-fill MRS data in the time domain.*

Description

Zero-fill MRS data in the time domain.

Usage

```
zf(x, factor = 2)

## S3 method for class 'list'
zf(x, factor = 2)

## S3 method for class 'mrs_data'
zf(x, factor = 2)

## S3 method for class 'basis_set'
zf(x, factor = 2)
```

Arguments

x input mrs_data or basis_set object.
factor zero-filling factor, factor of 2 returns a dataset with twice the original data points.

Value

zero-filled data.

zf_xy *Zero-fill MRSI data in the k-space x-y direction.*

Description

Zero-fill MRSI data in the k-space x-y direction.

Usage

```
zf_xy(mrs_data, factor = 2)
```

Arguments

mrs_data MRSI data.
factor zero-filling factor, a factor of 2 returns a dataset with twice the original points in the x-y directions. Factors smaller than one are permitted, such that a factor of 0.5 returns half the k-space points in the x-y directions.

Value

zero-filled data.

Index

* datasets

spant_mpress_drift, [144](#)

abfit_opts, [8](#), [11](#)
abfit_opts_v1_9_0, [11](#)
acquire, [12](#)
add_noise, [12](#)
align, [13](#)
apodise_xy, [13](#)
append_basis, [14](#)
append_coils, [14](#)
append_dyns, [15](#)
apply_axes, [15](#)
apply_mrs, [16](#)
apply_pvc, [16](#)
Arg.mrs_data, [17](#)
array2mrs_data, [17](#)
auto_phase, [18](#)

back_extrap_ar, [19](#)
basis2mrs_data, [19](#)
bbase, [20](#)
bc_als, [21](#)
bc_constant, [21](#)
beta2lw, [22](#)

calc_coil_noise_cor, [22](#)
calc_coil_noise_sd, [23](#)
calc_ed_from_lambda, [23](#)
calc_peak_info_vec, [24](#)
calc_sd_poly, [24](#)
calc_spec_diff, [25](#)
calc_spec_snr, [25](#)
check_lcm, [26](#)
check_tqn, [26](#)
circ_mask, [27](#)
collapse_to_dyns, [27](#)
comb_coils, [28](#)
comb_fit_list_fit_tables, [29](#)
comb_fit_list_result_tables, [29](#)

comb_fit_tables, [30](#)
comb_metab_ref, [30](#)
Conj.mrs_data, [31](#)
conv_mrs, [31](#)
crop_spec, [32](#)
crop_td_pts, [32](#)
crop_xy, [33](#)
crossprod_3d, [33](#)

decimate_mrs_fd, [34](#)
decimate_mrs_td, [34](#)
def_acq_paras, [35](#), [121](#), [137](#), [138](#), [140](#), [142](#)
def_fs, [36](#)
def_ft, [36](#)
def_N, [36](#)
def_nuc, [37](#)
def_ref, [37](#)
dicom_reader, [37](#)
diff_mrs, [38](#)
downsample_mrs_fd, [39](#)
downsample_mrs_td, [39](#)

ecc, [40](#)
elliptical_mask, [40](#)
est_noise_sd, [41](#)

fd2td, [41](#)
fd_conv_filt, [42](#)
fit_amps, [42](#)
fit_diags, [43](#)
fit_mrs, [43](#)
fit_res2csv, [45](#)
fp_phase, [45](#)
fp_phase_correct, [46](#)
fp_scale, [46](#)
fs, [47](#)
ft_dyns, [47](#)
ft_shift, [48](#)
ft_shift_mat, [48](#)
gausswin_2d, [49](#)

gen_F, 49
 gen_F_xy, 50
 get_1h_brain_basis_paras, 50
 get_1h_brain_basis_paras_v1, 51
 get_1h_brain_basis_paras_v2, 51
 get_1h_brain_basis_paras_v3, 52
 get_2d_psf, 52
 get_acq_paras, 53
 get_dyns, 53
 get_even_dyns, 54
 get_fh_dyns, 54
 get_fit_map, 55
 get_fp, 55
 get_guassian_pulse, 56
 get_head_dyns, 56
 get_lcm_cmd, 57
 get_metab, 57
 get_mol_names, 57
 get_mol_paras, 58
 get_mrs_affine, 60
 get_mrsi2d_seg, 58
 get_mrsi_voi, 59
 get_mrsi_voxel, 59
 get_mrsi_voxel_xy_psf, 60
 get_odd_dyns, 61
 get_ref, 61
 get_seg_ind, 62
 get_sh_dyns, 62
 get_slice, 63
 get_subset, 63
 get_svs_voi, 64
 get_tail_dyns, 65
 get_td_amp, 65
 get_tqn_cmd, 66
 get_uncoupled_mol, 66
 get_voi_cog, 67
 get_voi_seg, 67
 get_voi_seg_psf, 68
 get_voxel, 68
 grid_shift_xy, 70
 gridplot, 69
 gridplot.mrs_data, 69

 hsvd, 70
 hsvd_filt, 71
 hsvd_vec, 72
 hz, 72

 ift_shift, 73

 ift_shift_mat, 73
 Im.mrs_data, 74
 image.mrs_data, 74
 img2kspace_xy, 75
 int_spec, 76
 interleave_dyns, 76
 inv_even_dyns, 77
 inv_odd_dyns, 77
 is.def, 78
 is_fd, 78

 kspace2img_xy, 79

 l2_reg, 79
 lb, 80
 lw2alpha, 81
 lw2beta, 81

 mask_dyns, 82
 mask_xy, 82
 mask_xy_mat, 83
 mat2mrs_data, 83
 max_mrs, 84
 max_mrs_interp, 84
 mean.mrs_data, 85
 mean_dyn_blocks, 86
 mean_dyn_pairs, 86
 mean_dyns, 85
 mean_mrs_list, 87
 median_dyns, 87
 Mod.mrs_data, 88
 mrs_data2basis, 88
 mrs_data2mat, 89
 mrs_data2vec, 89
 mvfftshift, 90
 mviftshift, 90

 n2coord, 91
 Ncoils, 91
 Ndyns, 91
 nifti_flip_lr, 92
 Npts, 92
 Nspec, 93
 Nx, 93
 Ny, 93
 Nz, 94

 ortho3, 94
 ortho3_inter, 95

peak_info, 96
pg_extrap_xy, 97
phase, 98
plot.fit_result, 98
plot.mrs_data, 100
plot_bc, 102
plot_slice_fit, 102
plot_slice_fit_inter, 103
plot_slice_map, 103
plot_slice_map_inter, 104
plot_voi_overlay, 106
plot_voi_overlay_seg, 106
ppm, 107
precomp, 107
print.fit_result, 108
print.mrs_data, 108

qn_states, 109

rats, 109
Re.mrs_data, 110
re_weighting, 121
read_basis, 111
read_basis_ac, 111
read_ima_coil_dir, 112
read_ima_dyn_dir, 112
read_lcm_coord, 113
read_mrs, 113
read_mrs_tqn, 114
read_siemens_txt_hdr, 115
read_tqn_fit, 116
read_tqn_result, 116
recon_twix_2d_mrsi, 117
rectangular_mask, 117
rep_array_dim, 118
rep_dyn, 118
rep_mrs, 119
resample_img, 119
resample_voi, 120
reslice_to_mrs, 120
reson_table2mrs_data, 121
rm_dyns, 122

scale_amp_molal_pvc, 122
scale_amp_molar, 123
scale_amp_ratio, 123
scale_amp_water_ratio, 124
scale_mrs_amp, 124
scale_spec, 125

sd, 125
sd.mrs_data, 126
seconds, 126
seq_cpmg_ideal, 127
seq_mega_press_ideal, 127
seq_press_ideal, 128
seq_pulse_acquire, 129
seq_pulse_acquire_31p, 129
seq_slaser_ideal, 130
seq_spin_echo_ideal, 130
seq_spin_echo_ideal_31p, 131
seq_steam_ideal, 131
set_def_acq_paras, 132
set_lcm_cmd, 132
set_lw, 133
set_mask_xy_mat, 133
set_precomp_mode, 134
set_precomp_verbose, 134
set_ref, 134
set_td_pts, 135
set_tqn_cmd, 135
shift, 136
shift_basis, 136
sim_basis, 137
sim_basis_1h_brain, 137
sim_basis_1h_brain_press, 138
sim_basis_tqn, 139
sim_brain_1h, 139
sim_mol, 140
sim_noise, 141
sim_resonances, 142
sim_zero, 143
sort_basis, 143
spant (spant-package), 7
spant-package, 7
spant_abfit_benchmark, 144
spant_mpress_drift, 144
spant_simulation_benchmark, 145
spec_op, 145
spin_sys, 146
spm_pve2categorical, 146
ssp, 147
stackplot, 147
stackplot.fit_result, 148
stackplot.mrs_data, 149
sub_mean_dyns, 151
sum_coils, 151
sum_dyns, 152

sum_mrs, [152](#)
sum_mrs_list, [153](#)
svs_1h_brain_analysis, [153](#)
svs_1h_brain_batch_analysis, [154](#)

td2fd, [155](#)
td_conv_filt, [156](#)
tdsr, [156](#)

varpro_3_para_opts, [157](#)
varpro_basic_opts, [158](#)
varpro_opts, [158](#)
vec2mrs_data, [159](#)

write_basis, [160](#)
write_basis_tqn, [160](#)
write_mrs, [161](#)
write_mrs_nifti, [161](#)

zero_fade_spec, [162](#)
zero_nzoc, [162](#)
zf, [163](#)
zf_xy, [163](#)